PLEASE RETURN TO LIBRARIAN
B-8210 M.S. 47-24
MANUAL # 4

DATUM

TIMING DIVISION



# INSTRUCTION MANUAL
# MODEL 9300A
# TIME CODE
# GENERATOR/TRANSLATOR
# PART NUMBER 9300-7030

PLEASE RETURN TO LIBRARIAN
ORG. B-0210 M.S. 47-24
MANUAL # 4

Digitized by the Internet Archive
in 2025

https://archive.org/details/manualsplus_08025

# ADDENDUM

In addition to the basic 9300 Time Code Generator/Translator, the 9300-7030 contains the following options and/or modifications:

1. PARALLEL OUTPUTS (Binary)
   a. See Assembly Number 16271 and 16992 for logic.
   b. 10 bit binary milliseconds, 17 bit binary STOD.
   c. Outputs are TTL positive true.
   d. Sample time pulse is normally true pulsing to a logic "0" (GND) for approximately 1.5 μsec. At update time (1 KPPS rate).
   e. Output connector is J5.
   f. See Table 1 of this addendum for pin assignments.

2. INTERNAL STANDBY BATTERY POWER
   a. Provides power to basic generator assembly.
   b. Provides greater than one-half (1/2) hour of standby operation without a loss of "generated time".
   c. See following pages for option description.
   d. See Drawing Number 9300-8295 for Power modification.

## STANDBY POWER OPERATION

### FUNCTIONAL DESCRIPTION

This unit contains a rechargeable battery and associated charger and regulator. In the event of primary power loss the internal battery will sustain the basic timekeeping circuitry operational for a minimum of one-half (1/2) hour. The charger operates from the input power line and is energized whenever the front panel power switch is in the ON position.

The power for the basic generator assembly is supplied from this charger/regulator circuit. Whenever input line power is temporarily lost, the internal battery automatically begins supplying power to the basic assembly so that time continues to be generated. If line power is restored before the battery power fails, there should be no loss of generated time, other assemblies will become operational again, and the battery will begin to recharge.

CAUTION: Do NOT place the front POWER switch to the ON position whenever the AC power cord is disconnected as this will cause the internal battery to discharge.

TABLE 1

OUTPUT PIN CONNECTIONS

CONNECTOR J5

17 BIT BINARY STOD

10 BIT BINARY MILLISECONDS

| PIN | SIGNAL | PIN | SIGNAL |
|---|---|---|---|
| 1 | $ms2^0$ | 19 | $S2^8$ |
| 2 | $ms2^1$ | 20 | $S2^9$ |
| 3 | $ms2^2$ | 21 | $S2^{10}$ |
| 4 | $ms2^3$ | 22 | $S2^{11}$ |
| 5 | $ms2^4$ | 23 | $S2^{12}$ |
| 6 | $ms2^5$ | 24 | $S2^{13}$ |
| 7 | $ms2^6$ | 25 | $S2^{14}$ |
| 8 | $ms2^7$ | 26 | $S2^{15}$ |
| 9 | $ms2^8$ | 27 | $S2^{16}$ |
| 10 | $ms2^9$ | 28 | |
| 11 | $S2^0$ | 29 | |
| 12 | $S2^1$ | 30 | |
| 13 | $S2^2$ | 31 | |
| 14 | $S2^3$ | 32 | |
| 15 | $S2^4$ | 33 | |
| 16 | $S2^5$ | 34 | Sample Time |
| 17 | $S2^6$ | 35 | GND |
| 18 | $S2^7$ | 36 | GND |

NOTE:

1. The Model 9300 is shipped for use with 115V AC operation unless identified for 220/230 VAC at AC power connector. See next page for changes to 220 VAC operation.




1. Jumper #1 For 220 VAC Operation
2. Jumper #2 For 115 VAC Operation
3. Jumper #3 For Lo Line Voltage
4. Jumper #4 For Normal Line Voltage
5. Jumper #5 For Hi Line Voltage

TABLE OF CONTENTS


| | | |
|---|---|---|
| I | SYSTEM DESCRIPTION | I-1 |
| | 1.1 General | I-1 |
| | 1.2 Time Code Generator | I-1 |
| | 1.3 Time Code Translator | I-1 |
| | 1.4 Physical | I-2 |
| II | SPECIFICATIONS | |
| | 2.1 Inputs | II-1 |
| | 2.2 Outputs | II-1 |
| | 2.3 Time Base | II-2 |
| | 2.4 Environment | II-3 |
| | 2.5 Physical | II-3 |
| III | OPERATING PROCEDURES | |
| | 3.1 Generator Mode | III-1 |
| | 3.2 Translate Mode | III-1 |
| | 3.3 Bypass Operation | III-2 |
| | 3.4 Direction Control | III-2 |
| | 3.5 Input Code Polarity Control | III-2 |
| | 3.6 Internal Filter Control | III-2 |
| | 3.7 Tape Search Operation (Optional) | III-3 |
| | 3.8 5 Rate Slow Code (Optional) | III-3 |
| | 3.9 Input Code Select (Optional) | III-3 |
| | 3.10 Advance/Retard (Optional) | III-3 |
| | 3.11 External Start (Optional) | III-4 |
| | 3.12 Detailed Bypass Operation | III-5 |
| IV | ADJUSTMENTS | IV-1 |

TABLE OF CONTENTS (Continued)


| | | |
|---|---|---|
| V | THEORY OF OPERATION | V-1 |
| | 5.1 Logic Description and Used | V-1 |
| | 5.2 General | V-2 |
| | 5.3 Detailed Logic Description | V-4 |
| VI | MAINTENANCE | VI-1 |
| VII | LIST OF DRAWINGS | VII-1 |
| VIII. | LIST OF MATERIALS | VIII-1 |

# SECTION I

## SYSTEM DESCRIPTION

1.1 The Model 9300 Time Code Generator/Translator is designed to perform two basic functions. First, the unit generates a time code in suitable form for recording on magnetic tapes or paper charts. Secondly, the unit is capable of reading the recorded time when played back from a magnetic tape or other sources. The standard format includes BCD seconds, minutes, hours and days only in both the generator and translator modes.

### 1.2 TIME CODE GENERATOR

As a Time Code Generator the Model 9300 develops a serial, coded time code, modulated to allow recording on magnetic tape or to allow convenient distribution to remote users. The IRIG Format B is used so that the unit is compatible with many other existing facilities or other standard instrumentation equipment. The standard format is modified to include BCD seconds, minutes, hours and days only. Front panel controls allow the clock to be stopped, started or preset. Each digit of seconds, minutes, hours and days is settable to allow time-of-day or elapsed time operation. The basic clock accumulates time on a 24-hour basis and is accurately updated each second.

### 1.3 TIME CODE TRANSLATOR

When placed in the translate mode the unit will accept the standard IRIG B format either as generated in the Time Code Generator mode or as received from other sources. By using the standard IRIG Format B, the translator is usable in conjunction with other systems or projects. The unit automatically decodes the serial input code and provides a front panel display, serial pulse trains and optional digital outputs. Reading accuracy is better than 50 microseconds when reading in the forward playback mode.

A synchronization mode, selectable from the front panel, provides noise rejection. This feature allows the selection of "zero," "one," "two," "four," "eight," or "infinite" time frames bypass if input errors are detected. This feature is most important when digital outputs are required,

or tape search operation is desired. With "zero" selected each time frame is read. With one, two, four or eight selected, the unit is resynchronized only after the selected number of consecutive errored frames. With "infinite" selected, the unit updates from the carrier only and disregards the coded information. The unit must be synchronized in one of the other bypass positions prior to selecting the "infinite" mode.

## 1.4 PHYSICAL

The Model 9300 is constructed in a 1-3/4" package, requiring minimum 19" rack mounting or offering easy handling for desk mounting. A decimal display located on the front panel, shows either generated time or translated time depending on mode of operation. All operating mode controls are mounted on the front panel. Each display digit is individually presettable with a single thumbwheel switch and a pushbutton for each digit.

The circuitry of the Model 9300 consists of TTL and DTL type integrated circuits. Each element is mounted in a modular socket for ease in maintainability.

# SECTION II

# SPECIFICATIONS

## 2.1 INPUTS

### 2.1.1 J6 Power

a. 115/230 VAC ±10%

b. 48 to 420 Hz

### 2.1.2 J1 Code Input

| | | |
|---|---|---|
| a. | Format: | IRIG B BCD Time of Year (B122). (Control functions and straight binary seconds may be included in the code but are not recognized as valid data in the standard instrument.) |
| b. | Modulation Frequency: | 1 kHz |
| c. | Modulation Ratio: | 2:1 - 6:1 |
| d. | Amplitude: | 100 MV p-p to 10V p-p on the mark pulse. |
| e. | Input Z: | 100 K ohm minimum |
| f. | Frequency Range: | 10 Hz - 300 kHz |
| g. | Synchronization Accuracy: | Less than ±50 microseconds |

## 2.2 OUTPUTS

### 2.2.1 J2 IRIG B: BCD Time of Year (B122)

(NOTE: This output is only available when operating in the GEN mode.)

| | | |
|---|---|---|
| a. | Carrier Frequency: | 1 kHz sinewave |
| b. | Amplitude: | Adjustable from 0 to 10V p-p on the mark pulse. |
| c. | Modulation Ratio: | Adjustable from 2:1 through 4:1 |
| d. | External Load: | $\geq$ 600 ohms |

2.2.2 J3 Standard Pulse Rates

a. Rates:

| | |
|---|---|
| 1K pps | Pin 1 |
| 100 pps | Pin 2 |
| 10 pps | Pin 3 |
| 1 pps | Pin 4 |
| GND | Pin 6 |

b. Duty Cycle: 80/20%

c. 1K pps: 50/50% (In translator mode)

d. On Time Edge: Negative

e. Output Levels: Logic "0" $\leq$ 0.4 VDC
Logic "1" $\geq$ 2.4 VDC

f. Source Impedance: DTL/TTL Compatible

2.2.3 Parallel Outputs (Optional)

a. (J4) 44 bit BCD time of year (millisecond, S, M, H, D)

b. (J5) 32 bit time of year (S, M, H, D)

c. Output Levels: Logic "0" $\leq$ 0.4 VDC
Logic "1" $\geq$ 2.4 VDC

d. Source Impedance: DTL/TTL Compatible

e. Sample Time: Approximately 1.5 $\mu$sec pulse to a logic "0" at update time (data is changing during pulse time). Sample time rate is normally 1 pps or 1 kpps (seconds or milliseconds output resolution).

2.2.4 J3 - Bi-Level Five Rate Slow Code (Optional)

a. Format: DATUM Slow Code

b. Amplitude: Adjustable - 10V (maximum) on the "mark" pulse.

c. Source Impedance: 100 ohms

d. Pin 5 - CODE
Pin 6 - GND

2.3 TIME BASE

| | | |
|---|---|---|
| a. | Type: | Crystal Controlled Oscillator |
| b. | Frequency: | 1 MHz |
| c. | Stability: | $\pm 5 \times 10^{-6}$ |

2.4 ENVIRONMENT

| | | |
|---|---|---|
| a. | Temperature: | 0°C to +50°C |
| b. | Humidity: | Up to 95% relative |

2.5 PHYSICAL

| | | |
|---|---|---|
| a. | Panel Height: | 1-3/4 inches |
| b. | Chassis Width: | 17 inches |
| c. | Chassis Depth: | 18 inches |

## SECTION III

## OPERATING PROCEDURE

### 3.1 GENERATE MODE

a. Apply 115V AC power to J6

b. Turn on instrument by moving the PWR switch, located on the front panel, to the ON position.

c. Rotate the MODE switch to the HOLD position. (Display should be stationary.)

d. Preset the time of day using the following procedure:

   1. Start with the least significant digit (unit seconds) and in progression finish with hundreds of days.
   2. Select the number to be preset into each decade with the Preset thumbwheel switch.
   3. Press the pushbutton under each decade to enter the PRESET number into the output register.

e. Rotate the MODE switch to the GEN position. At the preset start time, press the START pushbutton.

f. The display will now update at a 1 pps rate and all outputs will be available on their respective output connectors.

### 3.2 TRANSLATE MODE

a. Apply power as in steps a and b of the GENERATE MODE procedure.

b. Place a standard 1 kHz modulated IRIG B code on BNC connector J1 located on the rear of the unit. It does not matter if the code format has been modified to remove the control functions or straight binary seconds as this portion of the time code is not used for decoding purposes in the 9300. (See 9300 specifications for modulation ratio, frequency range and amplitude requirements.)

c. Rotate the MODE switch to the TRANS position.

d. Place the FWD/REV switch to the FWD position.

e. After allowing approximately one minute after turn-on for the AGC to settle, the 9300 will autometically synchronize to the input time code.

3.3 BY-PASS OPERATION (See also paragraph 3.12)

a. Select TRANS. The 9300 will respond to each time frame of the input code. Any degradation of the input code may cause an erroneous reading on the 9300 Time Code Generator-Reader.

b. Select 4. The 9300 will sync to the input code, then automatically lock out its own sync circuits and just monitor the input code for time differences. Frame errors are counted; however, the 9300 synchronization is not disturbed unless four consecutive errored frames are counted. If frame errors are separated by a valid frame, the error counter is reset to zero; therefore, resynchronization can only take place on the fifth frame after counting four consecutive errored frames. This mode can be extremely useful when input time code is noisy or being derived from a poor or spliced tape.

c. oo BY-PASS. Note: Prior to selecting this position, the 9300 must be synchronized in either the TRANS, 1, 2, 4, or 8 position. After synchronization, rotate the MODE switch to the oo Bypass position. Once in this mode, all synchronizing functions are locked out and the 9300 will act as an elapsed time generator updating on the carrier rate of the input code.

3.4 DIRECTION CONTROL

The 9300 is provided with manual direction control and is operated by means of a front panel mounted toggle switch, INPUT FWD/REV. For forward operation place this switch in the FWD position. For reverse translation, place the switch in the REV direction.

3.5 INPUT CODE POLARITY CONTROL

The 9300 includes provisions to compensate for inverted polarity input codes. This is done with a front panel mounted toggle switch, INPUT +/-. For normal operation, this switch should be placed in the (+) position. For inverted polarity input codes, place the switch in the (-) position.

3.6 INTERNAL FILTER CONTROL

An internal 3 kHz low pass filter has been provided in the 9300, for use in playback (X1 speed ratio) operation. To activate the filter, place the front panel mounted FILTER IN/OUT switch to the IN position.

3.7 TAPE SEARCH OPERATION (Optional)

a. Connect the 9300 to the Tape Search unit as described in the Tape Search unit instruction manual.

b. Insure that the FWD/REV switch is in the FWD position and that the FILTER switch is in the IN position.

c. A logic "1" on Pin 45 of J4 will program the 9300 for forward operation, a logic "0", for reverse operation.

d. A logic "1" on Pin 49 of J4 will activate the low pass filter, a logic "0" will de-activate the filter.

e. A logic "0" Pin 47 of J4 will inhibit updating of the 9300.

3.8 5 RATE SLOW CODE (Optional)

The PRESET thumbwheel switch serves a dual function when the Slow Code option is installed. In addition to serving in the PRESET function, positions "1" through "5" select the desired frame period (see slow code drawing in Section V). Position "0" de-activates the Slow Code circuitry.

3.9 INPUT CODE SELECT (Optional)

Rotate the MODE A/B/E switch to program the 9300 to accept either IRIG A, IRIG B or IRIG E as the input code.

3.10 ADVANCE/RETARD (Optional)

a. Preset and start the generator as described in paragraph 3.1 above.

b. Sync an oscilloscope on the "on-time" edge of an external reference pulse (1 PPS).

c. Observe the "on-time" edge of the equivalent local pulse rate. If the local pulse appears to the right of the reference, the 9300 is "late." If the local pulse occurs to the left, the 9300 is "early."

d. Select the greatest Advance/Retard rate (refer to SWITCH & CONTROL LOGIC (11) drawing for rate identification) which will not overcorrect for the offset in one second. For example: for an offset of 5 milliseconds, the proper rate would be 1 millisecond/second, as 10 milliseconds/sec would overcorrect.

e. If the local pulse is "early," press the RET pushbutton. If the local pulse is "late," press the ADV pushbutton. Observe that the local pulse appears to move toward the reference pulse.

f. When the local pulse is within one second correction capability, select the next slowest correction rate.

g. Continue in this manner until the local pulse is alligned to within the maximum resolution of the Advance/Retard circuit.

3.11 EXTERNAL START (Optional)

a. Connect the external start pulse (1 PPS) to the INPUT BNC on the front panel. Place the WWV/DC switch in the appropriate position in accordance with the type signal to be used. Observe that the TICK indicator blinks at a 1 PPS rate.

b. If a WWV "tick" is being used, rotate the LEVEL control to the maximum counter-clockwise position. Adjust this potentiometer clockwise to obtain a steady blinking of the TICK indicator. Setting the control more clockwise than required to obtain a reliable indication may result in an unreliable start.

c. Preset the generator as described in steps 3.1. Rotate the MODE switch to the GEN position.

d. After the "Tick" which occurs one second prior to the preset start time, press the ARM pushbutton. The ARMED indicator will light.

e. The next "Tick Pulse" will start the generator.

## 3.12 DETAILED BY-PASS OPERATION

When this switch is set to "0" (TRANSLATE), the instrument monitors the input code and responds to each time frame of the input code. If the coded input is erroneous, the unit outputs the incorrect input value on both the visual display and the optional BCD output. However, the ERROR indicator is enabled (because a difference exists between the input and internal time values). This error status will remain until a subsequent code frame is input which is in agreement with the internal time value.

When this switch is set to "4", the instrument monitors the input code and if one or more frames are in error (up to 4), continues to properly update the displayed and BCD outputs by utilizing the 1 kHz carrier of the time code. Two (2) conditions affecting the ERROR indicator are as follows:

a. Less than four (4) consecutive 'erroneous' frames. The ERROR indicator is energized as long as a difference in time value exists between the input code and the internal time registers. At the end of a frame received in agreement with the internal time value, the ERROR indicator is de-energized.

b. Four (4) or more consecutive 'erroneous' frames.

   The ERROR indicator is energized as long as a difference in time value exists between the input code and the internal time registers. During the fifth consecutive frame, the time value

of the input code is entered into the internal time register. If the sixth consecutive frame of the input agrees with the updated time value in the internal time register, the ERROR indicator is de-energized at the end of this frame. However, if the sixth frame of the input code does NOT agree with the updated time value in the internal register, the input code value is again entered into the internal register and the next frame is again examined for agreement with the 'new' time value. The ERROR indicator remains energized and each subsequent frame time value is entered until time value agreement is found.

When the switch is set to "∞" (infinity), the instrument acts simply as an elapsed time generator, updated from its last time value by the carrier input. The ERROR indicator is energized when a difference in time value exists between the input time code and the internal time register and is de-energized at the end of the first frame found to be in agreement. Entering of input code time value(s) is inhibited whenever the switch is in the "∞" position.

Thus, the ERROR indicator is energized whenever (irrespective of switch position) a time value difference is detected between the code and the internal time register. Further, this status is de-energized at the end of the first subsequent code frame time value found in agreement with the internal time register. Therefore, the effect of the switch positions is to allow entering (jamming) of the input time code value into the internal time register under the following conditions:

a. "0" - each frame
b. "1" - the frame following a detected 'errored' frame
c. "2" - the frame following two (2) consecutive detected 'errored' frames
d. "4" - the frame following four (4) consecutive detected 'errored' frames
e. "8" - the frame following eight (8) consecutive detected 'errored' frames
f. "∞" - never

Finally, from the above examples, it may be discerned that the 'meaning' of the energized state of the ERROR indicator is that a difference in time value exists between the input code time value and the internal register time value and that the de-energized state of this status means there is no detected difference in these values.

# SECTION IV
# ADJUSTMENTS

The following is a list of adjustments which are basic to the 9300 Time Code Generator/Reader and includes those assemblies which are basic options. In the case of "Potentiometers," they are set at the factory to a nominal setting as indicated in ( ). However, the user should refer to the top assembly drawing for the location of these variables and adjust them for users specific requirements.

1. SINEWAVE SHAPER/MODULATOR ASSEMBLY
   a. R17 Level Adjustment. Range 0 to 10V peak to peak on the mark amplitude of the output code (3V p-p).

   b. R15 Modulation Ratio Adjustment. Range 2:1 - 4:1 mark to space ratio on the output code (3:1).

   c. R7 Phase Adjustment. Sets the phase of the carrier frequency so there is no discontinuity when amplitude modulation takes place.

2. POWER SUPPLY ASSEMBLY
   a. R10 adjusts the output level of the +5 volt regulator. Should be set to +5V ±2%.

3. SLOW CODE ASSEMBLY (Optional)
   a. R12 adjusts the output level (+6V mark amplitude)

# SECTION V

# THEORY OF OPERATION

## 5.1 LOGIC DESCRIPTION AND USE

The 9300 is depicted by several drawings. One of these is the top assembly drawing which shows the physical location of the assemblies that are contained within the instrument. This print should be used to locate connectors on the rear panel and for quick reference to the physical location of any of the assemblies or controls.

In the title block of each logic print is a circled number. For instance, the IRIG basic print (Minor Time) has circled number (8) in the title block. The IRIG basic print (Major Time) has circled number (9). The LED display has circled (12) in the title block. Except for terms originating within the drawing being studied, this reference number will precede each term, showing the sheet of logic upon which it originated. To use these numbers. simply observe the term, look at the term reference number in front of the term, then select the print that has this reference number in the title block. This print will show the point of origin of the term you are trying to find. This provides a convenient means of getting back and forth from various pages of these logics.

Each time a term reference number will refer you back to the source of that signal. In each of the logics there will be a number such as A4, A8, A11, etc. These number refer to the physical location on this assembly for that particular integrated-circuit element. In order to determine a physical location of an integrated circuit, one would merely refer to the top assembly drawing. In the lower left-hand corner of this drawing, each assembly contained within the instrument is listed, prefixed with a code letter, (Ⓐ Ⓑ Ⓒ etc.) then, by referencing the mechanical view of the top of the instrument, look for the board labeled with that code letter. Examine the board until the desired integrated circuit is located.

All references in this discussion will be based on the circled term reference numbers located in the title blocks of all logic prints. The reader should be familiar with the above before preceeding.

## 5.2 GENERAL

The Model 9300 is both a time generator and a time translator. A time generator is a device which takes a referenced frequency and divides it so as to accumulate or "count" time intervals. A time translator is a device which requires a serial coded input and "decodes," or "translates" this input to some other form, usually parallel time data.

In order to better understand the logic organization of the 9300, let's first review the basic configuration of typical timing units.

Figure 5-1 shows a simplified diagram of a typical Time Code Generator. The significant sections of a Time Code Generator are:

a. Frequency Source - Usually a crystal-controlled oscillator.

b. Minor Time Counters - The purpose of these counters is to develop scan terms and rates required to develop the serial code format or to be used for parallel outputs. They also supply a 1-pps signal that is used to update the Major Time Accumulator.

c. Major Time Accumulator - This section is a counter whose function is to store the time-of-year data. It is incremented by the 1 pps clock output of the frequency dividers. Its outputs are buffered and used for parallel outputs or they are scanned by the encoder and outputted in a serial format.

d. Counter Control - This section synchronizes the time accumulator and includes switches to select and enter the time-of-day into the Major Time Accumulator.

e. Parallel-to-Serial Converter - This section consists of scan gates that serialize the contents of the accumulator into a continous pulse train.

TYPICAL TIME CODE GENERATOR




FIGURE 5-1

f. Formatter - This section uses pulse rates from the minor time counter to obtain the pulse widths and index pulses required to provide the format defined by the type of time code being generated. This format is then usually combined with a sinewave to provide an amplitude-modulated signal.

g. Output Amplifier - This section provides the required output drive and signal levels of the formatter output.

h. Display - This section interfaces the generator with the operator.

Figure 5-2 shows a simplified diagram of a typical Time Code Translator. The significant points to a Time Translator are:

a. Input Amplifier - Usually this is an AGC type amplifier. Its function is to provide a constant amplitude signal to the decode and detection circuitry.

b. Serial to Parallel Converter - This is the heart of the unit. Its function is to detect digital data in the input format and assign it to storage in the time accumulator. This portion contains the necessary circuits to synchronize the frequency dividers.

c. Frequency Dividers - These counters divide the carrier frequency. Once synchronized by the decoding circuitry in the serial-to-parallel section, this counter provides the terms necessary to index the digital data contained in the input code. This allows the locating of each code bit and the proper assignment to accumulator storage. Also important, they provide a 1 pps signal to update the Time Accumulator.

d. Time Accumulator - This counter stores the value being read from the input code. It is updated with the 1 pps signal from the frequency dividers and is permuted to count in the format of the input time code (usually seconds, minutes, and hours). Day-of-year may sometimes be provided if required

TYPICAL TIME CODE TRANSLATOR




FIGURE 5-2

and it is contained in the input time code. The Time Accumulator is the basis for most outputs required by the unit.

e. Display - This section takes the Time Accumulator data and displays it for the user.

Now if we combine the two functions, taking advantage of circuitry found common to both, we obtain a Time Code Generator/Translator (Figure 5-3). Logic functions which are common, i.e., those which need not be duplicated are:

a. Frequency dividers (all of those in the translator and at least half of those in the generator).
b. Time Accumulator
c. Display

Of course, the power supply and chassis are shared.

## 5.3 DETAILED LOGIC DESCRIPTION

This description will be referenced only to the term reference numbers that are contained within the title block of each individual logic print. Before proceeding, the reader should be familiar with paragraph 5.1, LOGIC DESCRIPTION AND USE.

### (1) AGC

The automatic gain control amplifier assembly contains the input amplifier and the code strippers required to normalize the input and derive the necessary clock signals for the decoder.

The AGC amplifier is wideband so as to make the unit operational where variations of input signal frequency as well as amplitude is experienced such as in tape search applications.

Generally if a translator is used as a single purpose unit such as to only translate code at a single rate and display it, the AGC circuits can be narrowband. To make the unit more adaptable to different types of applications, we have provided a 100 MV to 10 volt dynamic range and a frequency response of 25 Hz to 300 kHz. The circuit does not require adjustment over this range.

TYPICAL TIME CODE GENERATOR/TRANSLATOR




FIGURE 5-3

After the input signal is normalized by the AGC, preset level comparators develop clock signals used for decoding. ØA which occurs at the positive zero axis crossing of the carrier, is used throughout the unit for clocking and synchronization. ØC is the mark clock which occurs only each half cycle of the carrier modulation (mark amplitude cycles).

Figure 5-4 shows a typical modulated signal. Two cycles are modulated. Examples of ØA and ØC are shown relative to the signal. Observe also the other definitions provided.

(2) DECODER

This logic uses the terms ØA, ØB and ØC from the AGC (1) to reconstruct the D.C. envelope of the input code. The logic symbol identified as DF3 represents this reconstructed envelope.

A binary counter is used to count the number of "mark" cycles that are contained during each positive excursion of DF3. Whenever four or more "mark" cycles are counted, the term BIN1 (Binary 1) will go to a logic "one" indicating the presence of a Binary One in the code. When eight "mark" cycles have been counted, the term PIC (Position Identifier Count) will go to a logic "one". The coincidence of PIC with DF3 being clocked off causes the logic term identified as PID (Position Identifier Detector) to go to a logic "one" indicating the detection of one of the ten position identifiers contained within the IRIG format.

Once per frame, the terms PIC, PID and DF2 coincide. This occurs at plus nine milliseconds in IRIG B and the decoded combination is used to fire the frame sync one-shot (FS). This pulse is used to sync the minor time counter (8) to a count of nine. Thus causing the minor time counter to be synchronized with the input time code.


MODULATION POINT
MARK AMPLITUDE
POSITIVE AXIS CROSSING
SPACE AMPLITUDE
X
3X
SPACE = X
MARK = 3X
MARK TO SPACE RATIO 3:1
TYPICAL ØC SLICING LEVEL
EXAMPLE ØA
EXAMPLE ØC
TYPICAL MODULATED TIME CODE

FIGURE 5-4

(3) MODE CONTROL

This logic contains the steering logic necessary to program the unit for the generate or translate mode of operation and to condition the unit for forward or reverse translation and to accept normal or inverted polarity input code.

In the generate mode, the unit is programmed for forward operation. In the translate mode, forward or reverse translation is controlled by the FWD/REV switch on the front panel or via the rear panel (FWD*) if the optional parallel outputs are installed. A front panel switch conditions the unit to accept normal (+) or inverted (-) polarity input codes.

This logic also contains a four-bit serial-to-parallel converter which converts the serial time information (BIN1) from (2) and converts this data to four lines of parallel data (SF1, 2, 4, or 8) in the translate mode. In the generate mode, the contents of the PRESET thumbhweel switch are passed directly through. These outputs are bussed common to the "D" inputs of the major time accumulators on (9). This allows for presetting the desired start time when in the HOLD mode or for loading the time content from the input code when in the translate mode.

Also contained on this logic is a two-way, four-bit data selector used to select the appropriate clocks for the serial-to-parallel converter (SFS) and the milliseconds counter (CMSC*) as well as two synchronization pulses ($\overline{FS}$* and $\overline{GFS}$*) in the generate or translate mode of operation. The serial-to-parallel converter is clocked by the 1 MHz clock (MCC) in the generate mode and by a decoded term from the Decoder (2) in the translate mode. The milliseconds counter is clocked by either tmSC8 in the generate mode or by ØA* in the translate mode.

Portions of four logic elements C3, D3, D9 and F9 are cross-gated to form the RUN/HOLD latch. In the generate mode, rotating the MODE switch to the HOLD position causes $\overline{\text{HOLD}}$ to become a logic "0", stoping and resetting the minor time counter (8) and enabling major time preset push-buttons via the term $\overline{\text{PSE}}$.

An "exclusive-or" element, D8 pins 1, 2, and 3 provides for a low-pass filter in the AGC to be activated by either the front panel FILTER IN/OUT switch (1FSC) or via the rear panel ($\overline{\text{SEARCH}}$) from the optional parallel outputs.

(4) SCAN LOGIC

This logic is used to generate the load pulses necessary for strobing the parallel data from the serial-to-parallel converter on (3) into the major time counter (9).

Assignment to the proper group (seconds, minutes, hours or days) is accomplished by logic elements C5 and C7. Assignment to the proper portion of each group is accomplished by logic elements E6 and E7 which generate units data strobe pulses (UDSF, UDSR) and tens data strobe pulses (TDSF, TDSR) for both forward and reverse operation.

Forward or reverse strobes are selected by logic element D7. The two load pulses are factored by the one-shot SPG which limits the strobe pulses ($\overline{\text{SPA}}$ and $\overline{\text{SPB}}$) to a duration of approximately one microsecond. $\overline{\text{SPG}}$ inhibits the strobes in the generate mode; or, in the translate mode, until the selected number of errored frames (EC8) from sync mode logic (5) are counted.

(5) SYNC MODE

This logic performs as a digital filter to prevent erroneous information from being displayed or from disturbing the various outputs.

The output of the IRIG Encoder ($\overline{DCSC}$) (32) is serially compared with the comparable decoder output ($\overline{DF2}$). IF a discrepancy exists between the two, the error detector flip-flop ECD clocks "on". When ECD is reset at the end of the frame, the error counter element C10 is clocked one time. The setting of the MODE BYPASS switch (1, 2, 4, 8, oo) determines how many errored frames will be counted before the counter output EC8 goes true. When this occurs, the error counter clocks are inhibited and the scan logic is enabled, allowing the input data to be loaded into the major time counter and allowing the minor time counter to be re-synchronized via the term $\overline{GFS}$.

If a valid frame (ECD not clocking on) occurs before reaching the selected number of errored frames (EC8 not clocking true), the error counter is reset via the term $\overline{REC}$. Therefore, the units synchronization will not be distrubed until the selected number of errored frames have been counted.

With the MODE/BYPASS switch in the TRANS position, EC8 is held true continuously, therefore the unit is synchronized each frame. With oo selected, the unit is never synchronized to the incoming code and acts as a generator, using the input code carrier as a time base.

The sync mode circuitry is disabled in the generate mode and when operating in the reverse direction.

(7) TIME BASE

This logic provides the 1 MHz time base for the generator. Four time bases are available: Two different 1 MHz crystal oscillators, a 10 MHz crystal oscillator and a divide-by-ten element, or an optional external 1 MHz sine-wave input with a level converter. The output is a TTL 1 MHz pulse (MCC).

(8) MINOR TIME

This logic consts of a series of decade counting units (DCU's) which accept the 1 MHz clock from (7) and divides it to 100 KPPS ($\mu$sc8), 10 KPPS (hmsc8), 1 KPPS (tmsc8), 100 PPS (msc8), 10 PPS (hsc8), and 1 PPS (tsc8). The term $\overline{HOLD}$ prevents the minor time counter from updating and holds each decade reset when in the HOLD mode. Also contained on this logic are four buffers which isolate the four standard pulse rate outputs.

(9) MAJOR TIME

This logic consists of a series of UP/DOWN counters which accept the 1 PPS clock (cUSC) from (8). This clock is divided down to one-pulse-per-minute at B9 pin 6, one-pulse-per-hour at B7 pin 6., one pulse-per-day at B5 pin 2 and one pulse-per-thousand days at B2 pin 7.

The tens-of-seconds counter, B9, is forced to recycle at the end of sixty seconds by one-shot RTS which "fires" at a decoded count of sixty (TSC4·TSC2). Similarly, the tens-of-minutes counter, B7, is reset at sixty minutes by RTM and the hours counters B5 and B6 at twenty-four hours by RHC.

Presetting the major time to the desired start time in the HOLD mode or to the contents of the input time code in the translate mode is accomplished by lowering the preset pin 11 of the selected decade to a logic "0". This is done via the pushbuttons beneath the associated digit of the display in the HOLD mode and via the strobe pulses from (4) in the translate mode. When this is done, the selected decade is preset to the state of the four preset lines, SF1, 2, 4, and 8.

(10) DISPLAY DRIVERS

This logic consists of a series of four-to-seven line decoders which converts the four-line BCD output of the major time counter (9) to the seven-line format required by the L.E.D. Display (12).

(11) SWITCH & CONTROL LOGIC

This print serves as an interface drawing used to indicate interconnections between the various assemblies within the unit as well as illustrating the various input and output connectors, with the exception of the parallel outputs which are described in a separate logic description.

(12) LED DISPLAY

This logic consists of nine seven-segment Light Emitting Diode (LED) display units. Each converts the seven-segment outputs from (10) to a visible display for interface to the user.

IRIG B Encoder (32)

Terms from the minor time counter are used to sequence multiplexer chips A9 through A14. The output of the major time counter is then scanned and grouped into ten bit serial words, X0 through X4. X0 contains the serial time information of units of seconds and tens of seconds. X1 contains the serial time information of units of minutes and tens of minutes. X2, units hours and tens of hours, X3 unit days and tens of days, and X4, hundreds of days. The terms X0 through X4, are again serially selected bit by bit by means of IC A15 and outputted as the term $\overline{D}$ on pin 6 of A15. $\overline{D}$ now represents the time of year information in a serial form.

Although the data at this point is serial, it is still not in an IRIG B format. The IRIG B format is generated by the output term DCSC and the collection of gates that control this reset line on pin 4 of A7. DCSC is enabled at a 100 pps rate and clocked true by the 1000 pps clock applied to pin 12 of A7. The reset occurs whenever the enable term of pin 4 a A7 is set to a "one" state. This occurs at 2 milliseconds if neither a position identifier is contained at that particular period or a binary "1" is not present in the code. However, if a binary "1" is present in the serial time information being generated at A15, pin 6, the reset of DCSC is delayed until the count of 5, or 5 milliseconds.

At a 10 pps rate, at a count of 9, the DCSC reset enable is delayed for 8 counts, thus generating an 8 millisecond wide position identifier. Once per second, at T-zero time, A7 pin 5 (X0Y0) is set true. This generates the frame reference pulse of the IRIG B time code and prevents the first pulse of each frame period from being reset until a count of 8 milliseconds. The output of DCSC is buffered and presented as the DC shift code output.

On (32A) the output of A8 pin 6 is a 1 KC squarewave. The odd harmonics are filtered from the squarewave to generate a sinewave is modulated by the DC code envelope ($\overline{DCSC}$) by means of FET Q1 and IC A17. The output of A17, pin 1, is attenuated by a potentiometer, R17, which is used to set the level of the IRIG B modulated serial time code. The output amplifier consists of A17, Q2 and Q3. The gain is set by resistors R18 and R20 and is set to be a fixed gain of 10. The modulated output is available on E6.

## POWER SUPPLY (49)

The Power Supply furnishes regulated ±15V DC and +5V DC to the unit. The ±15V DC regulators are integrated circuit regulators with internal fault protection. The +5V DC regulator employs and LM305 voltage regulator and is of the switching type.

The LM305 is essentially an operational amplifier with a built-in Zener reference. When the voltage on pin 6 falls a few millivolts below that of the internal reference, Q1 and Q2 are turned on and the voltage on the 5-volt line begins to rise. Q1 and Q2 turn off as the voltage on A1-6 rises above the reference level. L1 tries to maintain constant current flow and current begins to flow through CR2. This continues until Q1 and Q2 are again turned on and the cycle is repeated.

The switching regulator is thus an efficient method of obtaining constant 5V DC from an unregulated source, since power is dissipated in Q1 only when it is on or changing states.

For 5 volts from a 23V source, Q1 is on approximately 25 percent of the time. Q3 and Q4 provide short circuit protection by forcing the regulator to decrease the output voltage when the current through R7 becomes excessive. When the output voltage becomes too high, CR5 conducts and CR6 is turned on. The current limit circuit then shuts down the regulator.

## OPTIONS

Described in the following paragraphs are some (but not all) of the options and capabilities which are available. For instance, Control Functions and/or Binary seconds can be encoded and inserted into the serial code formats or translated from the input codes. These particular capabilities, although not listed would most likely be used in conjunction with one or more of the other options.

### A-B-E CODE SELECT (13) (OPTION)

The Code Select option is used whenever multi code translation is required. Whenever the option is installed in the unit, a front panel switch allows the operator to select the IRIG code (A, B and or E) the unit is to translate.

### ADVANCE/RETARD (20) (OPTION)

When in the generator mode of operation this assembly, in conjunction with front panel switches, allows the operator to slew the internally generated update clock in order to align it with an external reference signal.

### EXTERNAL START (25) (OPTION)

Allows the unit to be started "on time" from an external WWV TICK signal or a DC pulse.

### 17 BIT BINARY CONVERTER (27) (OPTION)

Provides parallel buffered 17 bit Binary outputs (seconds, minutes, hours) of the major time counter. 10 bits of Binary milliseconds can also be provided.

SLOW CODE (29) (OPTION)

Converts parallel BCD information (major time), in conjunction with a front panel switch, to a bi-level 5 rate serial Slow Code format.

PARALLEL OUTPUTS (30) (OPTION)

Provides parallel buffered BCD outputs of the major and or minor time counter contents. Also provides for other output timing signals and for external control of the Time Code Translator (e.g. Tape Search Control) if required.

IRIG A ENCODER (31) (OPTION)

This option provides for the generation of the IRIG A Time Code Format (A132). The operation of this assembly is the same as for IRIG B (32). However, since the code rate is 1000 PPS the input timing terms are different and the pulse widths mentioned are decreased by a factor of ten.

IRIG E ENCODER (35) (OPTION)

This option provides for the generation of an IRIG E Time Code Format (E112). The operation of this assembly is the same as for IRIG B (32). However, since the code rate is 10 PPS the input timing terms are different and the pulse widths are increased by a factor of ten.




TYPICAL MODULATED CARRIER (10000 Hz)

## IRIG FORMAT 'A' – GENERAL

1. **TIME FRAME:** 0.1 second
2. **CODE DIGIT WEIGHTING OPTIONS:** BCD, SB or both:
   a. Binary Coded Decimal Time-of-Year CODE WORD – 34 binary digits.
      (1) Seconds, minutes, hours, days and 0.1 seconds. Recycles yearly.
   b. Straight Binary Time-of-Day CODE WORD – 17 binary digits.
      (1) Seconds only. Recycles each 24 hours. (86399)
3. **CODE WORD STRUCTURE:**
   a. **BCD.** Word begins at INDEX COUNT 1. Binary-coded elements occur between POSITION IDENTIFIER ELEMENTS (seven for seconds; seven for minutes; six for hours; ten for days; four for 0.1 seconds) until the CODE WORD is complete. A POSITION IDENTIFIER occurs between decimal digits in each group to provide separation for visual resolution.
   b. **SB.** Word begins at INDEX COUNT 80. Seventeen binary-coded elements occur, with a POSITION IDENTIFIER between the 9th and 10th binary-coded elements.
4. **LEAST SIGNIFICANT DIGIT:** Occurs first, except for fractional seconds information, which occurs following the day-of-year information.
5. **ELEMENT RATES AVAILABLE:**
   a. 1000 per second (basic Element rate)
   b. 100 per second (POSITION IDENTIFIER rate)
   c. 10 per second (Frame rate)
6. **ELEMENT IDENTIFICATION:**
   a. "On-Time" reference point for each Element is its leading edge.
   b. INDEX MARKER duration: 0.2 milliseconds (Binary Zero or uncoded Element)
   c. CODE DIGIT duration: 0.5 milliseconds (Binary one)
   d. POSITION IDENTIFIER: 0.8 milliseconds
   e. REFERENCE MARKER: Two consecutive POSITION IDENTIFIERS.

   (The "on-time" point, to which the CODE WORD refers, is the leading edge of the second POSITION IDENTIFIER.)
7. **RESOLUTION:** 1 millisecond (unmodulated); 0.1 millisecond (modulated).
8. **CARRIER FREQUENCY:** 10 kHz when modulated.

**IRIG STANDARD FORMAT A**
**SIGNAL A00**
**1000 PPS CODE**
**REFERENCE IRIG DOCUMENT 104-70**




## IRIG FORMAT 'B'—GENERAL

1. **TIME FRAME:** 1.0 second.
2. **CODE DIGIT WEIGHTING OPTIONS:** BCD, SB or both:
   a. Binary Coded Decimal Time-of-Year CODE WORD — 30 binary digits.
      (1) Seconds, minutes, hours and days. Recycles yearly.
   b. Straight Binary Time-of-Day CODE WORD — 17 binary digits.
      (1) Seconds only. Recycles each 24 hours. (86399)
3. **CODE WORD STRUCTURE:**
   a. **BCD:** Word begins at INDEX COUNT 1. Binary-coded elements occur between POSITION IDENTIFIER ELEMENTS (seven for seconds, seven for minutes; six for hours; ten for days) until the CODE WORD is complete. A POSITION IDENTIFIER occurs between decimal digits in each group to provide separation for visual resolution.
   b. **SB:** Word begins at INDEX COUNT 80. Seventeen binary-coded elements occur with a POSITION IDENTIFIER between the 9th and 10th binary-coded elements.
4. **LEAST SIGNIFICANT DIGIT:** occurs first.
5. **ELEMENT RATES AVAILABLE:**
   a. 100 per second (basic Element rate)
   b. 10 per second (POSITIVE IDENTIFIER Rate)
   c. 1 per second (Frame Rate)
6. **ELEMENT IDENTIFICATION:**
   a. "On-Time" reference point for each Element is its leading edge.
   b. INDEX MARKER duration: 2 milliseconds (Binary zero or uncoded Element)
   c. CODE DIGIT duration: 5 milliseconds (Binary one)
   d. POSITION IDENTIFIER duration: 8 milliseconds
   e. REFERENCE MARKER — one per second: Two consecutive POSITION IDENTIFIERS.
   (The "On-Time" point, to which the CODE WORD refers, is the leading edge of the second POSITION IDENTIFIER.)
7. **RESOLUTION:** 10 milliseconds (unmodulated); 1 millisecond (modulated).
8. **CARRIER FREQUENCY:** 1 kHz when modulated.

**IRIG STANDARD FORMAT B**
SIGNAL B00
100 PPS CODE
**REFERENCE IRIG DOCUMENT 104-70**




TYPICAL MODULATED CARRIER

RECOMMENDED FREQUENCY, 100 Hz or 1000 Hz

## IRIG FORMAT 'E' — GENERAL

1. **TIME FRAME:** 10 seconds
2. **CODE DIGIT WEIGHTING:** BCD: Time-of-Year CODE WORD — 26 Binary Digits. Seconds, minutes, hours and days; recycles yearly.
3. **CODE WORD STRUCTURE:**
   BCD: Word begins at INDEX COUNT 6. Binary-coded Elements occur between POSITION IDENTIFIER ELEMENTS (three for seconds, seven for minutes; six for hours, ten for days) until the CODE WORD is complete. A POSITION IDENTIFIER occurs between decimal digits in each group to provide separation for visual resolution.
4. **LEAST SIGNIFICANT DIGIT:** Occurs first.
5. **ELEMENT RATES AVAILABLE:**
   a. 10 per second (basic Element rate)
   b. 1 per second (POSITION IDENTIFIER Rate)
   c. 0.1 per second (Frame Rate)
6. **ELEMENT IDENTIFICATION:**
   a. "On-Time" reference point for each Element is its leading edge.
   b. INDEX MARKER duration: 20 milliseconds (Binary zero or uncoded Element)
   c. CODE DIGIT duration: 50 milliseconds (Binary one)
   d. POSITION IDENTIFIER duration: 80 milliseconds (Refers to the leading edge of the succeeding Element).
   e. REFERENCE MARKER (one per 10 seconds): Two consecutive POSITION IDENTIFIERS.

   (The "On-Time' point, to which the CODE WORD refers, is the leading edge of the second POSITION IDENTIFIER.)
7. **RESOLUTION:** 100 milliseconds (unmodulated); 1 millisecond (modulated).
8. **CARRIER FREQUENCY:** 1 kHz or 100 Hz when modulated

**IRIG STANDARD FORMAT E**
SIGNAL E00
10 PPS CODE
REFERERCE IRIG DOCUMENT 104-70




| CODE | PULSE RATE | FRAME PERIOD | BINARY ZERO | BINARY ONE | FRAME REFERENCE PULSE |
|---|---|---|---|---|---|
| 1 | 50 PPS | 1 SEC | 4 MS | 10 MS | 20 MS |
| 2 | 10 PPS | 5 SEC | 20 MS | 50 MS | 100 MS |
| 3 | 5 PPS | 10 SEC | 40 MS | 100 MS | 200 MS |
| 4 | 1 PPS | 60 SEC | 200 MS | 500 MS | 1,000 MS |
| 5 | 1 PPS 10S | 10 MIN | 2 SEC | 5 SEC | 10 SEC |

datum inc.

# BI-LEVEL SLOW CODE REV. A

# SECTION VI
## MAINTENANCE

The 9300 Time Code Generator/Translator utilizes integrated circuits. There are no moving parts or parts with limited life. There is no periodic maintenance required for the unit under normal conditions. If the unit is exposed to unusual operating conditions such as high dust or high humidity environments, or if the unit is dropped or otherwise damaged, it may be necessary to perform certain inspections and/or repairs.

If it is necessary to inspect the unit, the following should be considered:

1. Always disconnect AC power before removing the instrument cover. To remove the cover, simply remove the screw at the rear panel and slide the cover off to the rear.

2. Make a thorough visual inspection of all circuitry and wiring.

3. Check for physical integrity of all components. Look for burned or cracked components, loose physical damage, leakage of insulation compounds or general physical damage. To aid in overall maintenance and repair, each integrated circuit is mounted in an individual modular socket. Removal or replacement is therfore convenient and easy.

   It should rarely be necessary to replace an integrated circuit; however, if replacement is attempted, be sure that all component leads enter the socket and that no leads are bent under the component or extended out from the socket.

   Check to see that all IC's are firmly mounted in the socket so that good electrical contact is made.

4. Check all switches and connectors for loose or broken wires.

5. If the internal component surfaces and components have an excessive amount of dust deposited on them, use a soft brush and a low pressure stream of air to remove any foreign material.

CAUTION

Do not clean PC boards or small internal components with a stiff brush or solvents since damage to the circuits may result. A high powered vacuum cleaner device should not be used on small internal components.

6. Wipe the external surfaces of the instrument with a soft damp cloth to remove dirt, fingerprints and other foreign material.

7. Replace the cover and reconnect the AC power and input connector. Check operation. If performance does not match or exceed the specifications listed, corrective maintenance is in order.

Printed Circuit Board Repair

Removal and insertion of IC components can be easily made as described above. Should it be necessary to replace conventional components which are soldered to the circuit board, cut the leads of the part near the lead holes. Using a low power (50 watts or less) soldering iron, apply heat sparingly to each cut lead. As soon as the solder melts, slip the lead from the hole and clean the hole with a tooth pick. Clean the board surfaces with isopropyl alcohol. Form the tinned leads of the replacement part and insert in cleaned holes, trimming the leads to extend 1/16-inch beyond the back surface of the board. Only 63/37 solder with a maximum

diameter of 1/16 inch should be used. Solder the leads to the board and use a hemostat, long nosed pliers, or other heat sink on the leads of all semiconductor devices and quarter-watt resistors. Allow the soldered junction to cool before removing the heat sink.

**WARNING**

Dangerous high voltages are present in the unit. Use caution at all times when the protective cover is removed.

SECTION VII

LIST OF DRAWINGS

| | | |
|---|---|---|
| 1. | Top Assembly | 9300-7030 |
| 2. | AGC (1) | 16085 |
| 3. | IRIG Basic (2) (3) (4) (5) (7) (8) (9) (10) | 16543 |
| 4. | Switch and Control Logic (11) | 9300-8294 |
| 5. | LED Display (12) | 16549 |
| 6. | Binary Converter (27) | 16271 |
| 7. | Parallel Outputs (30) | 16992 |
| 8. | IRIG B Encoder (32) | 16062 |
| 9. | Power Supply (49) | 16280 |
| 10. | Regulator | 17573 |
| 11. | Battery Charger | 15415 |
| 12. | Power Modification | 9300-8295 |

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |




REAR VIEW ROTATED 180°




7. POWER MODIFICATION 9300 8295
6. SWITCH & CONTROL LOGIC 9300-8294
5. WIRING DIAGRAM 803485 (BASIC)
4. WIRE LIST 803486 (BASIC), 807010 (UNIT)

(N) 17573S REGULATOR
(M) 16280-3 POWER SUPPLY
(L) 15415 BATT. CHARGER
(J) 16992-45 PARALLEL OUTPUTS
(I) 16271-1 BINARY CONV.
(C) 16085 AGC
(B) 16062-1 IRIG ENCODER (B)
(A) 16543-136 BASIC
(AA) 16549-1 DISPLAY

NOTES: UNLESS OTHERWISE SPECIFIED

J6-AC POWER INPUT
J5-PARALLEL OUTPUTS (BIN mS, BIN STOD)
J4-
J3-PULSE RATES
J2-CODE OUTPUT IRIG B
3. J1-CODE INPUT IRIG B
2. SLIDES & MOUNTING BRACKETS ARE OPTIONAL

THIS DATA IS CONFIDENTIAL TO DATUM INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES. TOL .XX ±.03 .XXX ±.010 ANGLES ±1/2°

TITLE: TIME CODE GENERATOR/TRANSLATOR

Datum inc.
1363 S STATE COLLEGE BLVD
ANAHEIM, CALIFORNIA 92806

| | | | |
|---|---|---|---|
| DWN | VFL | DES | |
| CHK | | ENGR | 5/8/78 |
| SCALE | NONE | FSC | 31160 |

SIZE C | 9300-7070 | SHT 1 OF 2 | REV

© BISHOP GRAPHICS INCORPORATED
ALL RIGHTS RESERVED UNDER A.I.A.


21.50-23.50 (REF)
17.00 REF
19.00 REF
1.00 (REF)
17.62 (REF)
BATTERY GC-826-1
BATTERY GC-826-1
C0231 OSC 1MHZ
EXT INT
A1 7408
A9 7408
A1 749
A3 A2
A4 749
A5 7405
A1 A13 A1
A1 A13
A12 A24 A11 A23
A2 R10
A1
T1P 3.5A
A3 7815
L
N
M
1. TOP COVER REMOVED FOR CLARITY
NOTES: UNLESS OTHERWISE SPECIFIED
THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT
C 9300-7030
SIZE SHT 2 OF 2 REV


REVISIONS
LTR
DESCRIPTION
DATE
APPROVED
INVERT SIGNAL
AGCP
FILTER
AGCF
AGC
DC
AC
GND
IN
GND
OUT
ØA
ØB
ØC
ØC
AS1
AS1
-5V*
(1A)
CR1 IN914A
CR2 IN705A @ 4.8V
CR3 IN914A
Q1 988704
Q2 988 103
Q3 P1087E
Q4 P1087E
Q5 P1087E
Q6 2N3565
A1
A2
A3
A4
A5
R1 1MEG
R2 120K
R3 91Ω
R4 5.1K
R5 10K
R6 10K
R7 10K
R9 120K
R10 33Ω
R11 10K
R12 5.1K
R13 5.1K
R14 5.1K
R15 120K
R16 7.5K
R17 560Ω
R18 510Ω
R19 75K
R20 5.1K
R21 1K
R22 1K
R23 47K
R24 18K
R25 2.7K
R26 1K
R27 1MEG
R28 10K
R29 6.8K
R30 1.5K
R31 3K
R32 2.7K
R33 1K
R34 5.1K
R35 120K
R36 10K
R37 1.2K
R38 1K
R39 2.7K
R40 5.1K
R41 10K
R42 1MEG
R43 1K
R44 390Ω
R45 1K
R47 270K
C1 .1μf
C2 1μf
C3 4.7μf 35V
C4 47μf
C5 .022μf
C6 10pf
C7 .01μf
C8 47μf
C9 47pf
C10 1500pf
C11A 220μf 4V
C11B 220μf 4V
C12 4.7μf 35V
C13 4.7μf 35V
C14 100μf
C15 1μf
C16 1μf
C17 4.7μf 35V
C22 470pf
THIS DATA IS CONFIDENTIAL TO DATUM INC AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT
UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOL: XX ± .03 XXX ± .010 ANGLES ± 1/2°
TITLE
AGC
(1)
datum inc.
1363 S. STATE COLLEGE BLVD. ANAHEIM, CALIFORNIA
DWN KAIN
CHK
ENGR
DES
SCALE NONE
DWG 31160
B
16085
G
SIZE
SHT 1 OF 2

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |
| A | ADDED C22 | 9-27-72 | R.F. |
| B | ADDED R20 TO SCHEMATIC +E WAS +$V_S$ | 1-11-73 | [illegible] |
| C | Q3,4,5 WERE 2N4342 | 6-13-73 | R.F. |
| D | ADDED C11A & C11B | 7-13-73 | [illegible] |
| E | Q1 WAS 988703 | 9-12-73 | R.F./C.N |
| F | C12 & C13 WERE 1μf | 9-21-73 | [illegible]/C.N |
| G | R3 WAS TO +E, ADDED E1 | 11-26-73 | [illegible]/R.S. |




⚠5 -1 C7 IS .001μf.

⚠1 WIRE TO +15 OR +5V AS REQUIRED

⚠4 THIS POINT GROUNDED TO INVERT SIGNAL - REVERSE MODE

⚠3 SEE PARALLEL OUTPUT SCHEM FOR PIN NUMBER

⚠2 REMOVE FOR REMOTE OR HIGHSPEED OPERATION

| PART NO | MFR | REF |
|---|---|---|
| SN7405 | NATIONAL | A5 |
| μA749 | FAIRCHILD | A1, A4 |
| LM311H | NATIONAL | A2, A3 |

THIS DATA IS CONFIDENTIAL TO DATUM, INC AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOL .XX ± .02 .XXX ± .010 ANGLES ± 1/2°

TITLE: AGC

(1A)

| | | | | |
|---|---|---|---|---|
| DWN KAIN | 7/13/72 | DES RF | 7/12/72 | |
| CHK [illegible] | 7/14/72 | ENGR [illegible] | 10/25 | |
| SCALE NONE | | FSC 31260 | | |

Datum inc.
1363 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92806

B | 16085 | G

SIZE | SHT 2 OF 2







NOT USED




| DASH NO | DESCRIPTION |
|---|---|
| 6 | GEN OPTION |
| 5 | 10MHZ CRYSTAL OSC |
| 4 | CO251 OSC |
| 3 | CO231 OSC |
| 2 | EXT OSC |
| 1 | DAYS |
| — | BASIC S-M-H |

NOTES: UNLESS OTHERWISE SPECIFIED

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |

| PART NO | MFR | REF DES |
|---|---|---|
| 899-1-R6K | BECKMAN | C6, C8 |
| 1M311D | NATIONAL | A1 |
| MC12061P | MOTOROLA | D1 |
| 9374-DC | FAIRCHILD | A2-A10 |
| N8281A | SIGNETICS | C10, E11 |
| N8280A | SIGNETICS | E5, F4-F7, C1 |
| N7486A | ↕ | C3, D8 |
| N7473A | ↕ | E10 |
| N7442B | SIGNETICS | E6 |
| SN7432N | T.I. | D6 |
| N7411A | SIGNETICS | C9 |
| N7410A | ↕ | D11 |
| N7408A | ↕ | D9, F8, F9 |
| N7404A | ↕ | D3 |
| N7400A | SIGNETICS | D2, D10, A11 |
| SN74156N | T.I. | C5, C7 |
| SN7474N | ↕ | E9, F11 |
| SN7425N | ↕ | E8 |
| SN74194N | ↕ | C2 |
| SN74192N | ↕ | B2-B10, E4 |
| SN74157N | ↕ | C4, D7, E7 |
| SN74123N | ↕ | D5, B11 |
| SN74H106N | ↕ | D4 |
| SN74H103N | T.I. | F10 |
| SN74122N | TI | C11 |

| PART NO | MFR | REF DES |
|---|---|---|

THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT.

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOL .XX ± .03 .XXX ± .010 ANGLES ± 1/2°

TITLE: IRIG BASIC (2) (DECODER)

DWN IC 6/24/74 DES

CHK Rml 6/24/74 ENGR K. Stroud 6/24/74

SCALE NONE FSC 31160

Datum Inc.
1363 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92806

B 16543 C

SIZE SHT 1 OF 8 REV

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |
| A | ADDED C26, D4-12 WAS GND PER CO# 2180 | 5-8-75 | RM |




⚠2 WITH SYNC GEN OPTION, REMOVE JUMPER BETWEEN E1 AND E3, JUMPER E1 TO E2.

NOTES: UNLESS OTHERWISE SPECIFIED

THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT.

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOL: XX ± .03, XXX ± .010, ANGLES ± 1/2°

TITLE: IRIG BASIC (MODE CONTROL) ③

| | | | |
|---|---|---|---|
| DWN | IC | 9/24/74 | DES |
| CHK | RM | 9/26/74 | ENGR JS Strickland 12/16/74 |
| SCALE | NONE | FSC | 31160 |

Datum inc. 1363 S. STATE COLLEGE BLVD. ANAHEIM, CALIFORNIA 92806

B | 16543 | C

SIZE | SHT 2 OF 8 | REV

DIETZGEN 1MM 10

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |




NOTES: UNLESS OTHERWISE SPECIFIED

THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT.

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOL: .XX ± .03 .XXX ± .010 ANGLES ± 1/2°

TITLE

# IRIG BASIC (SCAN LOGIC)

4

| | | | | | |
|---|---|---|---|---|---|
| DWN | IC | 6/24/74 | DES | | |
| CHK | Rol | 6/26/74 | ENGR | D McCord | 12/[illegible] |
| SCALE | NONE | | FSC | 31160 | |

datum Inc.
1303 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92806

B | 16543 | C

SIZE | SHT 3 OF 8 | REV

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |




⚠ IF DAYS OPTION IS NOT SUPPLIED:
E9-12 IS CONNECTED TO tSC2
E9-11 IS CONNECTED TO hSC8

NOTES UNLESS OTHERWISE SPECIFIED

THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES
TOL .XX ± .03
.XXX ± .010
ANGLES ± 1/2°

TITLE: IRIG BASIC (SYNC MODE) (5)

| | | | |
|---|---|---|---|
| DWN | IC | 6/25/74 | DES |
| CHK | RM | 6/26/74 | ENGR |
| SCALE | NONE | FSC | 31160 |

Datum Inc.
1363 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92806

| SIZE | | DWG NO | | REV |
|---|---|---|---|---|
| B | SHT 4 OF 8 | 16543 | | C |




NOTES: UNLESS OTHERWISE SPECIFIED

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |

THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT.

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES
TOL: .XX ± .03
.XXX ± .010
ANGLES ± 1/2°

TITLE
# IRIG BASIC (TIME BASE)
(7)

| | | | | |
|---|---|---|---|---|
| DWN | IC | 6/25/74 | DES | |
| CHK | RM | 6/26/74 | ENGR | 12/6/74 |
| SCALE | NONE | | FSC | 31160 |

Datum inc.
1363 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92803

B 16543 C

SIZE SHT 5 OF 8 REV

EIETZGEN 1NEM 10

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |
| B | C11 WAS 74123 PER CO#2277 | 9-9-75 | RM |
| C | REVISED PER C.O. 2747 | 6-18-76 | IC |




3 WHEN SYNC GEN OPTION IS USED ALL -6 TERMS ORIGINATE ON 15

NOTES: UNLESS OTHERWISE SPECIFIED

THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT.

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES
TOL: .XX ± .03
.XXX ± .010
ANGLES ± 1/2°

TITLE
IRIG BASIC
8 (MINOR TIME)

| | | | |
|---|---|---|---|
| DWN | IC | 7/25/74 | DES |
| CHK | [illegible] | 8/15/74 | ENGR [illegible] 12/16/74 |
| SCALE | NONE | FSC | 31160 |

Datum Inc.
1363 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92806

| SIZE | DWG | REV |
|---|---|---|
| B | 16543 | C |

SHT 6 OF 8


REVISIONS
LTR
DESCRIPTION
DATE
APPROVED
SUS
STS
SUM
STM
SUH
STH
SF8
SF4
SF2
SF1
RTS
RTM
RHC
CUSCU
CUSCd
E27
E28
E31
E30
+5V*
B10
B9
B8
B7
B6
B5
USC1
USC2
USC4
USC8
TSC1
TSC2
TSC4
UMC1
UMC2
UMC4
UMC8
TMC1
TMC2
TMC4
UHC1
UHC2
UHC4
UHC8
THC1
THC2
COH
R9
5.6K
C10
33PF
TSC2
TSC4
A11
B11
C9
330PF
HOLD
FWD
D9
TMC2
TMC4
R10
5.6K
C11
33PF
C13
330PF
THC2
UHC4
R11
5.6K
C12
33PF
SUD
STD
SHD
E16
E18
E21
RHC
COH
B4
B3
B2
UDC1
UDC2
UDC4
UDC8
TDC1
TDC2
TDC4
TDC8
HDC1
HDC2
HDC4
HDC8
-1 ASSY
NOTES: UNLESS OTHERWISE SPECIFIED
THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT.
TITLE
IRIG BASIC
(MAJOR TIME)
9
DWN MARTINEZ
6/26/74
DES
CHK
ENGR
SCALE NONE
FSC 31160
datum Inc.
1363 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92806
B
16543
C
SIZE
SHT 7 OF 8
REV




NOTES: UNLESS OTHERWISE SPECIFIED

THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT.

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOL: XX ± .03 XXX ± .010 ANGLES ± 1/2°

TITLE: IRIG BASIC (10) DISPLAY DRIVERS

| | | | |
|---|---|---|---|
| DWN IC | 6/25/74 | DES | |
| CHK | 6/26/74 | ENGR | 12/16/74 |
| SCALE NONE | | FSC 31160 | |

Datum Inc.
1363 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92806

B | 16543 | C

SIZE | SHT 8 OF 8 | REV

| POS. | MODE SW. |
|---|---|
| 1 | HOLD |
| 2 | GEN |
| 3 | READ |
| 4 | FB1 |
| 5 | FB2 |
| 6 | FB4 |
| 7 | FB8 |
| 8 | FB∞ |










| POL SW | |
|---|---|
| POS 1 | + |
| POS 2 | − |

| DIRECTION SW | |
|---|---|
| POS 1 | FWD |
| POS 2 | REV |

| FILTER SW | |
|---|---|
| POS 1 | IN |
| POS 2 | OUT |



















TERMS ⑪ REFERENCED TO THIS PRINT AND NOT SHOWN ARE FOR INTERNAL REFERENCE ONLY.

NOTES: UNLESS OTHERWISE SPECIFIED

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |

THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT.

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOL .XX ± .03 .XXX ± .010 ANGLES ± 1/2°

TITLE

⑪ SWITCH & CONTROL LOGIC (9300-7030)

| DWN | VFL | 2-7-78 | DES | |
|---|---|---|---|---|
| CHK | | | ENGR | 2/8/78 |
| SCALE | NONE | | FSC | 31160 |

datum inc.
1363 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92806

SIZE B | 9300-8294 | REV

SHT 1 OF 1

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |
| – | ADDED -4 & -5 | 10-21-77 | CC |




-5 LEDS ARE YELLOW, H/P 5082-7660
-4 LEDS ARE GREEN, H/P 5082-7670
-3 LEDS ARE FAIRCHILD FND-507
-2 LEDS ARE MONSANTO MAN6A
1. LEDS ARE H/P 5082-7650

NOTES: UNLESS OTHERWISE SPECIFIED

THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT.

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOL: .XX ± .01 .XXX ± .010 ANGLES ± 1/2°

TITLE: LED DISPLAY (12)

datum inc.
1363 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92806

| DWN | IC | 6/26/74 | DES | | |
|---|---|---|---|---|---|
| CHK | RM | 7/24/74 | ENGR | | 11/14/74 |
| SCALE | NONE | | FSC | 31160 | |

B 16549

SIZE | SHT 1 OF 1 | REV


REVISIONS
LTR
DESCRIPTION
DATE
APPROVED
USC2
TSC1
USC8
TSC4
UMC2
TMC1
UMC8
TMC4
TSC1
TMC1
USC4*
TSC2*
TSC4
UHC1*
UMC4*
TMC2*
TMC4
UHC2*
THC1*
UHC4
THC2*
UHC8*
TMC4
UHC1*
HB2
HB4
HB8
HB16
SB4
SB8
SB16
SB32
MB2
MB4
MB8
MB16
MB32
R1
R2
R3
R4
R5
R6
R7
R8
S2 1
S2 2
S2 3
S2 4
S2 5
S2 6
S2 7
S2 8
S2 9
S2 10
S2 11
S2 12
S2 13
S2 14
S2 15
S2 16
A15
A16
A17
A18
A19
A20
A21
A22
A23
A1
A2
A3
A4
A5
A6
A7
A8
A9
A10
A11
A12
(LOW POWER)
17 BIT BINARY
STOD CONVERTER
Datum Inc.
170 E. LIBERTY AVE.
ANAHEIM, CALIFORNIA
B
16271
SIZE
SHT 1 OF 2
REV
SCALE NONE
FSC 31160
DES
ENGR
CHK
OWN IC
3/9/72
UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOL .XX ± .03 .XXX ± .010 ANGLES ± 1/2°

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |



















| | | |
|---|---|---|
| US7408A | SPRAGUE | A6,18 |
| N8490A | SIGNETICS | A2,9,21 |
| N8281A | SIGNETICS | A1,13,14 |
| SN7480N | TEX.INST. | A3,4,15,16 |
| SN74LS83N | TEX.INST. | A5,7,8,10,11,17,19,20,22,23 |
| PART NO. | MFR. | REF. DES. |

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES
TOL: .XX ±.03
.XXX ±.010
ANGLES ±1/2°

TITLE
(27A) 17-BIT BINARY STOD CONVERTER (LOW POWER)

| | | | |
|---|---|---|---|
| DWN IC | 3/9/13 | DES | |
| CHK | | ENGR | |
| SCALE NONE | | FSC 31160 | |

Datum Inc.
170 E. LIBERTY AVE.
ANAHEIM, CALIFORNIA

B 16271

SIZE SHT 2 OF 2 REV

DIETZGEN 1986M10


MSEC OPTION -3
MSC1 MSC2 MSC4 MSC8 HSC1 HSC2 HSC4 HSC8 TSC1 TSC2 TSC4 TSC8
MS1 MS2 MS4 MS8 MS10 MS20 MS40 MS80 MS100 MS200 MS400 MS800
USC1 USC2 USC4
SEC1 SEC2 SEC4
-2
USC8 TSC1 TSC2 TSC4 UMC1 UMC2 UMC4 UMC8 TMC1 TMC2 TMC4 UHC1 UHC2
SEC8 SEC10 SEC20 SEC40 MIN1 MIN2 MIN4 MIN8 MIN10 MIN20 MIN40 HR1 HR2
UHC4 UHC8 THC1 THC2
HR4 HR8 HR10 HR20
UDC1 UDC2 UDC4 UDC8 TDC1
DA1 DA2 DA4 DA8 DA10
-1
TDC2 TDC4 TDC8 HDC1 HDC2 HDC4 HDC8
DA20 DA40 DA80 DA100 DA200 DA400 DA800
FWD* REC GO SAMPLE TIME SEARCH
FRP
R2 10K
C5 470PF
STP1 T≈ 1.5MS
CSTP1
+5V
+5*
C1 4.7uF 35V
C2 .1uF 10V
C3 4.7uF 35V
C4 .1uF 10V
R1 2.2K
C6 .01uF
-1 DAYS (J4) -4 BINARY STOD (J5)
-2 S-H (J4) -5 BINARY MS (J5)
-3 MS (J4) -6 SPARE OUTPUTS (J5)
REVISIONS
LTR DESCRIPTION DATE APPROVED
THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT.
UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOL .XX ± .03 .XXX ± .010 ANGLES ± 1/2°
TITLE
PARALLEL OUTPUTS (BCD)
datum inc.
1363 S. STATE COLLEGE BLVD. ANAHEIM, CALIFORNIA 92806
DRW VALENCIA 9/7/76
CHK
DES
INSP 10/7/76
SCALE NONE
ISS 31159
SIZE B
16992
SHT 1 OF 2
REV
N7408A SIGNETICS A2-11, A14-23
SN74123N TEX. INST. A1
PART NO. MFR ALTERNATE REF.
NOTES: UNLESS OTHERWISE SPECIFIED


-5
-4
-6
REVISIONS
LTR
DESCRIPTION
DATE
APPROVED
J5
MS2⁰
MS2¹
MS2²
MS2³
MS2⁴
MS2⁵
MS2⁶
MS2⁷
MS2⁸
MS2⁹
A20
A21
A22
BMS1
BMS2
BMS4
BMS8
BMS16
BMS32
BMS64
BMS128
BMS256
BMS512
USC1
S2¹
S2²
S2³
S2⁴
S2⁵
S2⁶
S2⁷
A22
A23
A8
BSEC⁰
BSEC¹
BSEC²
BSEC³
BSEC⁴
BSEC⁵
BSEC⁶
BSEC⁷
S2⁸
S2⁹
S2¹⁰
S2¹¹
S2¹²
S2¹³
S2¹⁴
S2¹⁵
S2¹⁶
A8
A9
A10
BSEC⁸
BSEC⁹
BSEC¹⁰
BSEC¹¹
BSEC¹²
BSEC¹³
BSEC¹⁴
BSEC¹⁵
BSEC¹⁶
OUTPUT 1
OUTPUT 2
OUTPUT 3
OUTPUT 4
OUTPUT 5
A10
A11
OUT 1
OUT 2
OUT 3
OUT 4
OUT 5
A24-4
A24-5
A2
SAMPLE TIME 2
+5V
R3
10K
C7
470PF.
CSTP2
STP2
T≈
1.5μS
A1
+5*
THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT.
UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES
TOL .XX ± .03
.XXX ± .010
ANGLES ± 1/2°
TITLE
PARALLEL OUTPUTS
(BINARY STOD)
30A
datum inc.
1363 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92806
DWN VALENCIA 9/7/76
CHK
DES
ENGR
SCALE NONE
PSC 31160
B
16992
SIZE
SHT 2 OF 2
REV


REVISIONS
LTR
DESCRIPTION
DATE
APPROVED
-1 DAYS OPTION
-2 OPTION
A14
A13
A12
A11
A10
A9
A15
A7
TSC8
TSC4
TSC2
TSC1
USC1
USC2
USC4
USC8
TSC1
TSC2
UMC1
UMC2
UMC4
UMC8
TMC1
TMC2
TMC4
UHC1
UHC2
UHC4
UHC8
THC1
THC2
UDC1
UDC2
UDC4
UDC8
TDC1
TDC2
TDC4
TDC8
HDC1
HDC2
HDC4
HDC8
.1C
.2C
.4C
.8C
CF1
CF2
CF3
CF4
CF5
CF6
CF7
CF8
CF9
X0
X1
X2
X3
X4
X5
XOYO
V1
CZC*
DCSC
TP1
DC CODE
R1
2.2K
+5V
C1
4.7uf.35V
C2
.1uf
C3
4.7uf.35V
C4
.1uf.
MSC1
MSC2
MSC4
MSC8
CMSC/TMSC8
CZC*
1*
D
X8+X9
TSC8 B
NOTES: UNLESS OTHERWISE SPECIFIED
THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT.
TITLE
IRIG B ENCODER
(32)
DWN KAIN 4/24/75
CHK 7/3/75
SCALE NONE
ENGR 7/3/75
FSC 31160
B
160162
A
SHT 1 OF 2
datum inc.
1363 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92805

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |
| A | R4 WAS 20.5K PER CO# 2759 | 2-3-77 | [illegible] |
| - | ADDED (11) REF.'S CF1-CF9 ON -2 | 11-14-77 | CC/[illegible] |




| BASIC | SEC, MIN, HOURS |
|---|---|
| -1 | SEC MIN HOURS DAYS |
| -2 | EXPANSION |
| -3 | LOW Z DRIVER |

5 REMOVE JUMPER FROM E4-E5 WHEN -3 OPTION IS USED.

4 GROUND WHEN 17 BIT BINARY NOT USED.

3 GROUND PIN 14 WHEN -2 OPTION IS NOT USED.

1 CUT ETCH AND GROUND PINS 12 & 15 WHEN DAYS OPTION IS NOT USED.

NOTES: UNLESS OTHERWISE SPECIFIED

| | | |
|---|---|---|
| N5558V | SIGNETICS | A17, A18 |
| N74151N | T.I. | A9-15 |
| N74107A | NATIONAL | A7 |
| N7432A | " | A6, 8 |
| N7411A | " | A5 |
| N7408A | " | A1, A4, A16 |
| N7400A | NATIONAL | A2, A3 |
| PART NO. | MFR | REF. DES. |

THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT.

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOL: XX ± .03 XXX ± .010 ANGLES ± 1/2°

TITLE: IRIG B ENCODER (32A)

DWN KAIN 6/26/75 | DES | CHK [illegible] 11/3/75 | ENGR [illegible] 7/8/76 | SCALE NONE | FSC 31160

Datum inc.
1333 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92805

B | 16062 | A

SIZE | SHT 2 OF 2 | REV

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |
| A | C4 WAS 948901 SELECTED 4.7μf | 6-26-73 | |
| B | CHANGED A2 PER CO 3576 | 6-24-77 | |




| | | | |
|---|---|---|---|
| -12 | +5V, +15V, -15V 100mA | C12, CRS2, R14 | 956082 |
| -11 | +5V ±12V | C12, CRS2, R14 | 956082 |
| A | INCLUDES ASSY 16742 | | |
| -10 | +5V, ±15V | C12, CRS2, R14 | 956082 |
| -9 | -1, -2, -5, CR-7 USED WITH 16742 | | |
| -8 | +5V, ±12, -15, +175 | C12 | 956088 |
| -7 | +5V, ±15V | C12, CRS2, R14 | 956116 |
| -6 | +5V, ±15V, +17.5V | C12 | 956088 |
| -5 | +5V, +12V, -15V | SEE NOTE 5. | 956082 |
| -4 | +5V, ±15V, +17.5V | | 956083 |
| -3 | +5V, ±15V | C12, CRS2, R14 | 956082 |
| -2 | +5V, +17.5V | A3, A3, C8, C9, C10, C11, CR7, CR8 | 956088 |
| -1 | +5 ONLY | A2, A3, C8, C9, C10, C11, C12, CR7, CRS2, R14, CR8 | 956082 |
| | | COMP 5 NOT USED | |

| | | | |
|---|---|---|---|
| | | COMP NOT USED | XFORMER USED |

NOTES: UNLESS OTHERWISE SPECIFIED

DASH NO.

DIMENSIONS ARE IN INCHES
TOL .XX ± .03
.XXX ± .010
ANGLES ± 1/2°

TITLE: POWER SUPPLY

(49)

DRN: EK
CHK:
SCALE: NONE

Datum Inc.
1363 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92806

B | 16280 | B

SHT 1 OF 2


REVISIONS
LTR DESCRIPTION DATE APPROVED
+23V INPUT
E4
L1 956045
Q1 TIP35A
Q2 2N2905A
R2 68Ω
CR2 MR820
R3 750K
R4 22Ω
A1
R5 47K
Q3 2N3645
Q4 2N3565
CR3 IN914A
R6 47K
R7 .1Ω, 3W
C6 .022μf 100V
C4 47μf 35V
CR5 IN752A 5.6V
R12 68Ω
CR6 MCR106-1
C5 .1μf 10V
R13 100Ω
C7 .1μf 10V
+5V
COMMON
R11 3.3K
R10 1K
R9 6.8K
C8 4.7μf 35V
CR7 IN4934
C9 47μf 35V
CR8 IN4934
A2
C10 4.7μf 35V
C11 4.7μf 35V
-15V
+15V
A3
USED ON -3, -4, -5, -6, -7, -8, -11, & -12 ASSY ONLY
1. +23V OR'ED WHEN -A ASSY USED.
2. -10 ASSY. A3 IS 7808, A2 IS 7910CB.
3. -5 & -8 ASSY. OUTPUT IS +12V, -10 ASSY OUTPUT IS ±8V
4. A3 ASSY. A3 IS UGA7812393 OR MC7812CP
5. A3 IS UGA7815393 OR MC7815CP
6. A2 IS MC7915CP OR 7915UC
7. A1 IS LM305
8. RESISTORS ARE 1/4 W 5%
NOTES: UNLESS OTHERWISE SPECIFIED
10. -12 ASSY : A2 IS 7915UC
9. -11 ASSY : A2 IS MC7912CP, A3 IS MC7812CP
TITLE
REGULATOR
49
datum inc.
1083 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92806
SCALE NONE
B 16280 B
SHT 2

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |




NOTES: UNLESS OTHERWISE SPECIFIED

| LM305 | NATIONAL | A1 |
|---|---|---|
| PART NO | MFR. | REF. DES. |

THIS DATA IS CONFIDENTIAL TO NATIONAL INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOL. XX ± .03 XXX ± .010 ANGLES ± 1°

TITLE: REGULATOR

| | | | | | |
|---|---|---|---|---|---|
| DWN | IC | 9/13/74 | DES | IC | 9/13/74 |
| CHK | RM | 9/14/74 | ENGR APPROVAL | | |
| SCALE | NONE | | | | |

Natural Inc. 1363 S. STATE COLLEGE BLVD ANAHEIM, CALIFORNIA 92806

| SIZE | DWG NO | REV |
|---|---|---|
| B | 17573 | |

SHT 1 OF 1

| | | |
|---|---|---|
| C | R3 WAS 10Ω | 1-4-77 |

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |
| A | CR2 WAS IN4005 | 10-5-71 | JC |
| - | ADDED NOTE 2 | 6-4-73 | JC |
| B | REVISE NOTES 1 & 2 | 6-21-73 | |




2. CURRENT LIMIT E6 TO E2 : 1.5A

1.

| ASSY | INPUT V (E3) | R2 | R3 | R4 | R6 | OUTPUT V (E4) |
|---|---|---|---|---|---|---|
| BASIC | +29V | 1Ω 1/2W | 3Ω | 21.5K | 1.50K | +18V |
| -1 | +29V | 1Ω, 1/2W | 3Ω | 21.5K | 1.50K | +18V |
| -2 | +29V | 1Ω, 1/2W | 3Ω | 6.98K | 1.00K | +12V – +13.5V |
| -3 | +15 | 1Ω, 3W | JPR | 8.87K | 1.50K | +9V |
| -4 | +23V | 1Ω, ½W | 3Ω | 6.98K | 1.00K | +12V – +13.5V |
| -5 | +23V | 27Ω, ½W | 3Ω | 6.98K | 1.00K | +12V – +15V |

| LM205 | | NATIONAL | A1 |
|---|---|---|---|
| PART NO. | ALTERNATE | MFR. | REF |

THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOL: .XX ± .03, .XXX ± .010, ANGLES ± 1/2°

TITLE: BATTERY CHARGER

datum inc.
170 E. LIBERTY AVE.
ANAHEIM, CALIFORNIA

| DWN | DES | | |
|---|---|---|---|
| CHK | | ENGR | |
| SCALE | | FSC 31160 | SIZE B | 15415 | C |
| | | | SHT / OF / | REV |

DIETZGEN 176 M-10

| REVISIONS | | | |
|---|---|---|---|
| LTR | DESCRIPTION | DATE | APPROVED |




NOTES: UNLESS OTHERWISE SPECIFIED

THIS DATA IS CONFIDENTIAL TO DATUM, INC. AND SHALL NOT BE REPRODUCED OR USED FOR ANY PURPOSE EXCEPT TO THE EXTENT PROVIDED BY CONTRACT.

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES
TOL: .XX ± .03
.XXX ± .010
ANGLES ± 1/2°

TITLE: POWER MODIFICATION (9300-7030)

datum inc.
1363 S. STATE COLLEGE BLVD.
ANAHEIM, CALIFORNIA 92806

| DWN | DES | ENGR | SIZE | DWG NO | REV |
|---|---|---|---|---|---|
| VFL 2-7-78 | | 2/8/78 | B | 9300-8295 | |
| CHK | | | | | |
| SCALE NONE | FSC 31160 | | SHT 1 OF 1 | | |

SECTION VIII

LIST OF MATERIALS

| | | |
|---|---|---|
| 1. | Time Code Generator/Translator | 9300-7030 |
| 2. | Time Code Generator/Translator | 9300-001 |
| 3. | AGC | 16085 |
| 4. | IRIG Basic | 16543-136 |
| 5. | LED Display | 16549-1 |
| 6. | Binary Converter | 16271-1 |
| 7. | Parallel Outputs | 16992-45 |
| 8. | IRIG B Encoder | 16062-1 |
| 9. | Power Supply | 16280-3 |
| 10. | Regulator | 17573S |
| 11. | Battery Charger | 15415 |

DATE: 1-23-78
DRAWN: R. FLOCK
CHK:

# MATERIAL LIST

datum inc.

JOB NO:
QUANTITY
REV

TITLE: TIME CODE GENERATOR / TRANS.
ASS'Y NO: 9300-7030
SHT 1 OF 1

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | REF. DES. | UNIT COST | LOT TOTAL |
|---|---|---|---|---|---|---|---|
| 1 | 9300-001 | BASIC ASSY STK | DATUM | 1 | | | |
| 2 | SK9300-7030 | SHIPPING KIT | " | 1 | | | |
| 3 | | | | | | | |
| 4 | 0540-4720 | DIODE IN4720 | " | 1 | | | |
| 5 | 1202-0202 | SWITCH DPDT | " | 1 | | | |
| 6 | 1704-1625-9P | PLUG 9P | " | 1 | | | |
| 7 | " -1625-9R | RECEPT 9P | " | 2 | | | |
| 8 | 1792-1560 | PIN | " | 9 | | | |
| 9 | " -1561 | SKT | " | 18 | | | |
| 10 | 2310-4002 | STANDOFF 5/16" | " | 4 | | | |
| 11 | " -4007 | " 1" | " | 4 | | | |
| 12 | 2901-0826 | BATTERY | " | 2 | | | |
| 13 | | | | | | | |
| 14 | 700546 | STIFFENER STK | " | 2 | | | |
| 15 | 703335-2 | BUTCH PLATE STK | " | 1 | | | |
| 16 | 704798 | BATTERY PLATE | " | 4 | | | |
| 17 | 705977 | REGULATOR BKT | " | 1 | | | |
| 18 | | | | | | | |
| 19 | 15415 | BATTERY CHARGER STK | " | 1 | | | |
| 20 | 16271-1 | BINARY CONVERTOR | " | 1 | | | |
| 21 | 16543-136 | BASIC | " | 1 | /1 | | |
| 22 | 16992-45 | PARALLEL OUTPUTS | " | 1 | | | |
| 23 | 17573S | REGULATOR STK | " | 1 | | | |
| | | | | | | | |
| | | | | | | | |
| | | | | | | | |

NOTES: /1 M/F 16543-16 IN BASIC ASSY.

BISHOP GRAPHICS/ACCUPRESS
REORDER NO. A-7967

DATE: 1-18-78
DRAWN: R. FLOCK
CHK:

# MATERIAL LIST

datum inc.

JOB NO:
QUANTITY
TITLE: TIME CODE GEN/TRANS BASIC
ASS'Y NO: 9300-001

REV: D
SHT 1 OF 2

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | REF. DES. | UNIT COST | LOT TOTAL |
|---|---|---|---|---|---|---|---|
| 1 | 0226-0104-1 | CAPACITOR .1uf @100V | DATUM | 1 | C101 | | |
| 2 | | | | | | | |
| 3 | 1202-0102 | SWITCH SPDT | " | 4 | | | |
| 4 | 1204-3903 | " P/B | " | 10 | | | |
| 5 | 1206-5112-N | " ROTARY | " | 1 | | | |
| 6 | 1212-7606 | " T/W | " | 1 | | | |
| 7 | 1299-7656-1 | BAND HDWE | " | 1 | | | |
| 8 | | | | | | | |
| 9 | 1704-1002 | RECEPT BNC | " | 2 | | | |
| 10 | " -1625-6R | " 6P | " | 1 | | | |
| 11 | 1792-1561 | SKT | " | 6 | | | |
| 12 | 1795-0001 | WASHER | " | 2 | | | |
| 13 | " -0002 | " | " | 2 | | | |
| 14 | | | | | | | |
| 15 | 2325-2005 | FASTENER | " | 2 | | | |
| 16 | 2524-5010 | KNOB | " | 1 | | | |
| 17 | | | | | | | |
| 18 | 700362 | CENTER SUPPORT STK | " | 1 | | | |
| 19 | 700364-2 | COVER STK | " | 2 | | | |
| 20 | 700546 | STIFFENER STK | " | 3 | | | |
| 21 | 703995 | MTG BKT STK | " | 2 | | | |
| 22 | 704757-2 | SIDE GUSSET STK | " | 2 | | | |
| 23 | 704899-1 | REAR PANEL STK | " | 1 | | | |
| 24 | | | | | | | |
| 25 | | | | | | | |
| 26 | | | | | | | |

NOTES:

BISHOP GRAPHICS/ACCUPRESS
REORDER NO. A-7967

DATE: 1-18-78
DRAWN: R. FLOCK
CHK:

# MATERIAL LIST

datum inc.

JOB NO:
QUANTITY
REV: D

TITLE: TIME CODE GEN/TRANS BASIC
ASS'Y NO: 9300-001
SHT 2 OF 2

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | REF. DES. | UNIT COST | LOT TOTAL |
|---|---|---|---|---|---|---|---|
| 27 | 705850 | FRONT PANEL STK | DATUM | 1 | | | |
| 28 | 705853 | COVER PLATE STK | " | 1 | | | |
| 29 | 705866-3 | LENS STK | " | 1 | | | |
| 30 | | | | | | | |
| 31 | 931500 | HANDLE STK | " | 2 | | | |
| 32 | | | | | | | |
| 33 | 170979 | P.C. BD. STK | " | 1 | | | |
| 34 | | | | | | | |
| 35 | 16062-1 | IRIG ENCODER | " | 1 | | | |
| 36 | 16085 | AGC STK | " | 1 | | | |
| 37 | 16280-3 | POWER SUPPLY STK | " | 1 | | | |
| 38 | 16543-16 | BASIC | " | 1 | | | |
| 39 | 16549-1 | DISPLAY STK | " | 1 | | | |

NOTES:

BISHOP GRAPHICS/ACCUPRESS
REORDER NO. A-7967

DATE: 3-6-75
DRAWN: RHE
CHK:

# MATERIAL LIST

Datum inc.

JOB NO:
QUANTITY:
REV G

TITLE: AGC

ASS'Y NO: 16085
SHT 1 OF 3

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | REF. DES. | UNIT COST | LOT TOTAL |
|---|---|---|---|---|---|---|---|
| 1 | 0102-0330 | RESISTOR 33Ω ¼W 5% | DATUM | 1 | R10 | | |
| 2 | " -0910 | " 91Ω " " | " | 1 | R3 | | |
| 3 | " -0391 | " 390Ω " " | " | 1 | R44 | | |
| 4 | " -0511 | " 510Ω " " | " | 1 | R18 | | |
| 5 | " -0561 | " 560Ω " " | " | 1 | R17 | | |
| 6 | " -0102 | " 1K " " | " | 7 | R21,22,26,33,38,43,45 | | |
| 7 | " -0122 | " 1.2K " " | " | 1 | R37 | | |
| 8 | " -0152 | " 1.5K " " | " | 1 | R30 | | |
| 9 | " -0202 | " 2K " " | " | 1 | R46 | | |
| 10 | " -0272 | " 2.7K " " | " | 3 | R25,32,39 | | |
| 11 | " -0302 | " 3K " " | " | 1 | R31 | | |
| 12 | " -0512 | " 5.1K " " | " | 8 | R4,8,12-14,20,34,40 | | |
| 13 | " -0682 | " 6.8K " " | " | 1 | R29 | | |
| 14 | " -0752 | " 7.5K " " | " | 1 | R16 | | |
| 15 | " -0103 | " 10K " " | " | 7 | R5-7,11,28,36,41 | | |
| 16 | " -0183 | " 18K " " | " | 1 | R24 | | |
| 17 | " -0473 | " 47K " " | " | 1 | R23 | | |
| 18 | " -0753 | " 75K " " | " | 1 | R19 | | |
| 19 | " -0124 | " 120K " " | " | 4 | R2,9,15,35 | | |
| 20 | " -0274 | " 270K " " | " | 1 | R47 | | |
| 21 | " -0105 | " 1M " " | " | 3 | R1,27,42 | | |
| 22 | 0104-0221 | " 220Ω ½W " | " | 1 | R48 | | |
| 23 | | | | | | | |
| 24 | 0220474 | CAPACITOR .47μf 35V | " | 2 | C4,8 | | |
| 25 | " -0105 | " 1μf " | " | 6 | C2,15,16,19-21 | | |
| 26 | " -0475 | " 4.7μf " | " | 5 | C3,12,13,17,18 | | |

NOTES:

DATE: 3-6-75
DRAWN: RHP
CHK:

# MATERIAL LIST

Datum inc.

JOB NO:
QUANTITY:
TITLE: AGC
ASS'Y NO: 16085

REV G
SHT 2 OF 3

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | REF. DES. | UNIT COST | LOT TOTAL |
|---|---|---|---|---|---|---|---|
| 27 | 0220-0107 | CAPACITOR 100Mf 10V | DATUM | 1 | C14 | | |
| 28 | 0221-0221 | " 220Mf 4V | " | 2 | C11A, 11B | | |
| 29 | 0225-0471 | " 470Pf | " | 1 | C22 | | |
| 30 | " -0152 | " 1500Pf | " | 1 | C10 | | |
| 31 | 0226-0100 | " 10Pf | " | 1 | C6 | | |
| 32 | " -0470 | " 47Pf | " | 1 | C9 | | |
| 33 | " -0103-1 | " .01Mf 100V | " | 1 | C7 | | |
| 34 | " -0203 | " .02Mf " | " | 1 | C5 | | |
| 35 | " -0104-1 | " .1Mf " | " | 1 | C1 | | |
| 36 | | | | | | | |
| 37 | 0301-7405 | FC N7405A | " | 1 | A5 | | |
| 38 | " -7749 | " X6A7749393 | " | 2 | A1,4 | | |
| 39 | " -9311-H | " LM311H | " | 2 | A2,3 | | |
| 40 | | | | | | | |
| 41 | 0500-0306 | DIODE 1N914A | " | 2 | CR1,3 | | |
| 42 | 0515-0705-1 | " 1N705A | " | 1 | CR2 | | |
| 43 | " -0752-1 | " 1N752A | " | 1 | CR4 | | |
| 44 | | | | | | | |
| 45 | 0550-7705 | TRANSISTOR 2N3565 | " | 1 | Q6 | | |
| 46 | 0555-6600 | " 2N3645 | " | 1 | Q7 | | |
| 47 | 0570-1087 | " P1087E | " | 3 | Q3-5 | | |
| 48 | " -8703 | " U1487E | " | 1 | Q2 | | |
| 49 | " -8704 | " 988704 | " | 1 | Q1 | | |
| 50 | | | | | | | |
| 51 | | | | | | | |
| 52 | | | | | | | |

NOTES:

DATE: 3-6-75
DRAWN: RHE
CHK:

# MATERIAL LIST

datum inc.

JOB NO:
QUANTITY:
REV G

TITLE: AGC
ASS'Y NO: 16085
SHT 3 OF 5

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | | | | REF. DES. | UNIT COST | LOT TOTAL | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 53 | 170B-3100-1 | SOCKET 14P | DATUM | 3 | | | | | | | |
| 54 | " -8000 | " 8P | " | 2 | | | | | | | |
| 55 | | | | | | | | | | | |
| 56 | 170574E | PC BOARD STK | " | 1 | | | | | | | |
| 57 | 170785NK | " STK | " | 1 | | | | | | | |

NOTES:

DATE: 10-16-74
DRAWN: GAE
CHK:

# MATERIAL LIST

datum inc.

JOB NO:
QUANTITY:
REV. C

TITLE: IRIG BASIC

ASS'Y NO: 16513-136

SHT 1 OF 2

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | | | | REF. DES. | UNIT COST | LOT TOTAL | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 1 | 0102-0151 | RESISTOR 150Ω 1/4W 5% | DATUM | 1 | | | | R3 | | | |
| 2 | " -0102 | " 1K " " | " | 1 | | | | R4 | | | |
| 3 | | | | | | | | | | | |
| 4 | " -0512 | " 5.1K " " | " | 1 | | | | R1 | | | |
| 5 | " -0562 | " 5.6K " " | " | 3 | | | | R9-11 | | | |
| 6 | " -0103 | " 10K " " | " | 1 | | | | R2 | | | |
| 7 | | | | | | | | | | | |
| 8 | 0126-R6K0 | " CHIP 6K | " | 2 | | | | C6,8 | | | |
| 9 | | | | | | | | | | | |
| 10 | 0220-0475 | CAPACITOR 4.7μf 35V | " | 7 | | | | C3,14-17,22,23 | | | |
| 11 | 0225-0330 | " 33Pf | " | 3 | | | | C10-12 | | | |
| 12 | " -0221 | " 220Pf | " | 2 | | | | C1,2 | | | |
| 13 | " -0331 | " 330Pf | " | 2 | | | | C9,13 | | | |
| 14 | 0221-0685 | " 6.8μf 35V | " | 1 | | | | C25 | | | |
| 15 | 0226-0104 | " .1μf 10V | " | 5 | | | | C18-21,24 | | | |
| 16 | | | | | | | | | | | |
| 17 | | | | | | | | | | | |
| 18 | | | | | | | | | | | |
| 19 | 0301-7H03 | IC SN74H103N | " | 1 | | | | F10 | | | |
| 20 | " -7H06 | " SN74H106N | " | 1 | | | * | D4 | | | |
| 21 | " -7123 | " SN74123N | " | 2 | | | * | B11, D5 | | | |
| 22 | " -7156 | " SN74156N | " | 2 | | | * | C5,7 | | | |
| 23 | " -7157 | " SN74157N | " | 3 | | | * | C4, D7, E7 | | | |
| 24 | " -7192 | " SN74192N | " | 10 | | | * | B2-10, E4 | | | |
| 25 | " -7194 | " SN74194N | " | 1 | | | * | C2 | | | |
| 26 | " -7400 | " N7400A | " | 3 | | | | A11, D2, 10 | | | |

NOTES:

DATE: 10-16-74
DRAWN: RAE
CHK:

# MATERIAL LIST

datum inc.

JOB NO:
QUANTITY:

REV C

TITLE: IRIG BASIC

ASS'Y NO: 16543-136

SHT 2 OF 2

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | | | | REF. DES. | UNIT COST | LOT TOTAL | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 27 | 0301-7404 | IC N7404A | DATUM | 1 | | | | D3 | | | |
| 28 | " -7408 | " N7408A | " | 3 | | | | D9, F8, 9 | | | |
| 29 | " -7410 | " N7410A | " | 1 | | | | D11 | | | |
| 30 | " -7411 | " N7411A | " | 1 | | | | C9 | | | |
| 31 | " -7425 | " SN7425N | " | 1 | | | | E8 | | | |
| 32 | " -7432 | " SN7432N | " | 1 | | | | D6 | | | |
| 33 | " -7442 | " N7442B | " | 1 | | | * | E6 | | | |
| 34 | " -7473 | " N7473A | " | 1 | | | | E10 | | | |
| 35 | " -7474 | " SN7474N | " | 2 | | | | E9, F11 | | | |
| 36 | " -7486 | " N7486A | " | 2 | | | | C3, D8 | | | |
| 37 | " -8280 | " N8280A | " | 5 | | | | E5, F4-7 | | | |
| 38 | " -8281 | " N8281A | " | 2 | | | | C10, E11 | | | |
| 39 | " -7122 | " SN74122 | " | 1 | | | | C11 | | | |
| 40 | " -9374 | " 9374DC | " | 9 | | | * | A2-10 | | | |
| 41 | | | | | | | | | | | |
| 42 | | | | | | | | | | | |
| 43 | | | | | | | | | | | |
| 44 | 1301-0001 | OSCILLATOR 1MHz | " | 1 | | | | Y1 | | | |
| 45 | | | | | | | | | | | |
| 46 | 1708-3897 | SOCKET 14P W/W | " | 27 | | | | | | | |
| 47 | " -3898 | " 16P " | " | 29 | | | * | | | | |
| 48 | | | | | | | | | | | |
| 49 | 2310-1591-B | MTG BLOCK | " | 2 | | | | | | | |
| 50 | | | | | | | | | | | |
| 51 | 170969 | PC BOARD | " | 1 | | | | | | | |

NOTES:

DATE: 7-26-76
DRAWN: R. FLOCK
CHK:

# MATERIAL LIST

datum inc.

JOB NO:
QUANTITY
REV

TITLE: LED DISPLAY
ASS'Y NO: 16549-1
SHT 1 OF 1

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | REF. DES. | UNIT COST | LOT TOTAL |
|---|---|---|---|---|---|---|---|
| 1 | 1708-0036 | HEADER | DATUM | 2 | | | |
| 3 | " -3788 | SKT | " | 9 | | | |
| 5 | 2205-0006 | LED DISPLAY | " | 9 | DS1-9 | | |
| 7 | 170937 | P.C. BD. STK | " | 1 | | | |

NOTES:

BISHOP GRAPHICS/ACCUPRESS
REORDER NO. A-7967

DATE: 3-7-73
DRAWN: R. Flock
CHK:

# MATERIAL LIST

datum inc.

JOB NO:
QUANTITY
REV

TITLE: 17 BIT BINARY STOD CONVERTER

ASS'Y NO: 16271-1
SHT 1 OF 1

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | | | | REF. DES. | UNIT COST | LOT TOTAL | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 1 | 0102-0102 | RESISTOR, 1K, 1/4W, 5% | DATUM | 1 | | | | R1 | | | |
| 2 | " -0152 | " 1.5K " " | " | 1 | | | | R2 | | | |
| 3 | | | | | | | | | | | |
| 4 | 0212-0104 | CAPACITOR .1uf @ 100V | " | 2 | | | | C3,4 | | | |
| 5 | 0220-0475 | " 4.7uf @ 35V | " | 3 | | | | C1,2,5 | | | |
| 6 | 0225-0121 | " 120pf @ 100V | " | 1 | | | | C6 | | | |
| 7 | | | | | | | | | | | |
| 8 | 0301-7583 | I.C. SN74LS83N | " | 10 | | | * | A5,7,8,10,11,17,19,20 | | | |
| 9 | | | | | | | | 22,23 | | | |
| 10 | " -7408 | " N7408A | " | 2 | | | | A6,18 | | | |
| 11 | " -7480 | " N7480A | " | 4 | | | | A3,4,15,16 | | | |
| 12 | " -8281 | " N8281A | " | 3 | | | | A1,13,14 | | | |
| 13 | " -8490 | " N8490A | " | 3 | | | | A2,9,21 | | | |
| 14 | | | | | | | | | | | |
| 15 | 1108-3897 | SKT 14P W/W | " | 12 | | | | | | | |
| 16 | " -3898 | " 16P " | " | 10 | | | * | | | | |
| 17 | | | | | | | | | | | |
| 18 | 170202 | P.C. BD. STK | " | 1 | | | | | | | |

NOTES:

BISHOP GRAPHICS/ACCUPRESS
REORDER NO A-7967

DATE: 8-31-7

DRAWN: RKE

CHK:

# MATERIAL LIST

datum inc.

JOB NO:

QUANTITY:

REV

TITLE: PARALLEL OUTPUT

ASS'Y NO: 16992-45

SHT 1 OF 1

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | | | | REF. DES. | UNIT COST | LOT TOTAL | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 1 | 0102-0222 | RESISTOR 2.2K ¼W 5% | DATUM | 1 | | | | R1 | | | |
| 2 | " -0103 | " 10K " " | " | 2 | | | | R2,3 | | | |
| 3 | | | | | | | | | | | |
| 4 | 0220-0475 | CAPACITOR 4.7μf 35V | " | 2 | | | | C1,3 | | | |
| 5 | 0225-0471 | " 470pf | " | 2 | | | | C5,7 | | | |
| 6 | 0226-0103-1 | " .01μf 100V | " | 1 | | | | C6 | | | |
| 7 | " -0104 | " .1μf 10V | " | 2 | | | | C2,4 | | | |
| 8 | | | | | | | | | | | |
| 9 | 0301-7123 | IC SN74123N | " | 1 | | | * | A1 | | | |
| 10 | " -7408 | " N7408A | " | 8 | | | | A2,8-10,20-23 | | | |
| 11 | | | | | | | | | | | |
| 12 | 1704-0036 | CONNECTOR 36P | " | 1 | | | | J5 | | | |
| 13 | | | | | | | | | | | |
| 14 | | | | | | | | | | | |
| 15 | 1708-3897 | SOCKET 14P W/W | " | 8 | | | | | | | |
| 16 | " -3898 | " 16P " | " | 1 | | | ** | | | | |
| 17 | | | | | | | | | | | |
| 18 | 703336 | COVR PLATE STK | " | 1 | | | | | | | |
| 19 | | | | | | | | | | | |
| 20 | 171112 | PC BOARD STK | " | 1 | | | | | | | |

NOTES:

DATE: 10-20-75
DRAWN: RAE
CHK:

# MATERIAL LIST

Datum inc.

JOB NO:
QUANTITY:
REV: A
TITLE: IRIG ENCODER
ASS'Y NO: 16062-1
SHT 1 OF 3

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | REF. DES. | UNIT COST | LOT TOTAL |
|---|---|---|---|---|---|---|---|
| 1 | 0102-0100 | RESISTOR 10Ω ¼W 5% | DATUM | 2 | R26,27 | | |
| 2 | " -0510 | " 51Ω " " | " | 1 | R25 | | |
| 3 | " -0222 | " 2.2K " " | " | 2 | R1,13 | | |
| 4 | | | | | | | |
| 5 | " -0332 | " 3.3K " " | " | 1 | R3 | | |
| 6 | " -0472 | " 4.7K " " | " | 1 | R12 | | |
| 7 | " -0103 | " 10K " " | " | 5 | R2,11,16,18,19 | | |
| 8 | " -0473 | " 47K " " | " | 3 | R6,10,14 | | |
| 9 | " -0104 | " 100K " " | " | 1 | R20 | | |
| 10 | 0115-2052 | " 20.5K " 1% | " | 1 | R8 | | |
| 11 | " -2262 | " 22.6K " " | " | 3 | R4,5,9 | | |
| 12 | 0154-5001 | " POT 5K | " | 3 | R7,15,17 | | |
| 13 | | | | | | | |
| 14 | 0201-0221 | CAPACITOR 220PF | " | 1 | C10 | | |
| 15 | 0212-0222 | " .0022μF 100V | " | 2 | C6,8 | | |
| 16 | " -0223 | " .022μF " | " | 2 | C7,9 | | |
| 17 | 0220-0475 | " 4.7μF 35V | " | 3 | C1,3,5 | | |
| 18 | | | | | | | |
| 19 | 0226-0104 | " .1μF 10V | " | 2 | C2,4 | | |
| 20 | " -0104-1 | " .1μF 100V | " | 2 | C11,12 | | |
| 21 | | | | | | | |
| 22 | 0301-5558 | IC N5558V | " | 2 | A17,18 | | |
| 23 | " -7107 | " SN74107N | " | 1 | A7 | | |
| 24 | " -7151 | " SN74151N | " | 6 | * A10-15 | | |
| 25 | " -7400 | " N7400A | " | 2 | A2,3 | | |
| 26 | " -7408 | " N7408A | " | 3 | A1,4,16 | | |

NOTES:

DATE: 10-20-75
DRAWN: QME
CHK:

# MATERIAL LIST

Datum inc.

JOB NO:
QUANTITY:
TITLE: IRIG ENCODER
ASS'Y NO: 16062-1

REV A
SHT 2 OF 2

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | | | | | REF. DES. | UNIT COST | LOT TOTAL | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| 27 | 0301-7411 | IC N7411A | DATUM | 1 | | | | | A5 | | | |
| 28 | " -7432 | " SN7432N | " | 2 | | | | | A6, 8 | | | |
| 29 | | | | | | | | | | | | |
| 30 | | | | | | | | | | | | |
| 31 | | | | | | | | | | | | |
| 32 | | | | | | | | | | | | |
| 33 | | | | | | | | | | | | |
| 34 | 0570-1087 | TRANSISTOR P1087E | " | 1 | | | | | Q1 | | | |
| 35 | | | | | | | | | | | | |
| 36 | 1206-2010 | TERMINAL | " | 4 | | | | | TP1-4 | | | |
| 37 | 1708-2034 | SOCKET 8P | " | 2 | | | | | | | | |
| 38 | " -3897 | " 14P W/W | " | 9 | | | | | | | | |
| 39 | " -3898 | " 16P " | " | 6 | | | | * | | | | |
| 40 | | | | | | | | | | | | |
| 41 | 170518 | PC BOARD STH | " | 1 | | | | | | | | |

NOTES:

DATE: 11-14-74
DRAWN: RME
CHK:

# MATERIAL LIST

Datum inc.

JOB NO:
QUANTITY:

REV C

TITLE: POWER SUPPLY +5V ±15V

ASS'Y NO: 16280-3

SHT 1 OF 3

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | REF. DES. | UNIT COST | LOT TOTAL |
|---|---|---|---|---|---|---|---|
| 1 | 0102-0220 | RESISTOR 22Ω ¼W 5% | DATUM | 1 | R4 | | |
| 2 | " -0680 | " 68Ω " " | " | 2 | R2,12 | | |
| 3 | " -0101 | " 100Ω " " | " | 1 | R13 | | |
| 4 | " -0332 | " 3.3K " " | " | 1 | R11 | | |
| 5 | " -0472 | " 4.7K " " | " | 1 | R1 | | |
| 6 | " -0682 | " 6.8K " " | " | 1 | R9 | | |
| 7 | " -0473 | " 47K " " | " | 2 | R5,6 | | |
| 8 | " -0754 | " 750K " " | " | 1 | R3 | | |
| 9 | 0125-0R10 | " .1Ω 3W | " | 1 | R7 | | |
| 10 | 0151-1001 | " POT 1K | " | 1 | R10 | | |
| 11 | | | | | | | |
| 12 | 0212-0223 | CAPACITOR .022μF 100V | " | 1 | C6 | | |
| 13 | 0219-0588 | " 5800μF 40V | " | 1 | C1 | | |
| 14 | 0220-0475 | " 4.7μF 35V | " | 3 | C8,10,11 | | |
| 15 | " -0476 | " 47μF 35V | " | 2 | C9,4 | | |
| 16 | | | | | | | |
| 17 | 0226-0103 | " .01μF 1000V | " | 2 | C101,102 | | |
| 18 | " -0104 | " .1μF 10V | " | 2 | C5,7 | | |
| 19 | | | | | | | |
| 20 | 0301-7815 | IC UGH7815393 | " | 1 | A3 | | |
| 21 | " -9305 | " LM305 | " | 1 | A1 | | |
| 22 | " -7915 | " MC7915CP | " | 1 | A2 | | |
| 23 | | | | | | | |
| 24 | 0500-0306 | DIODE 1N914A | " | 1 | CR3 | | |
| 25 | 0515-0752-1 | " 1N752A | " | 1 | CR5 | | |
| 26 | 0540-0106-1 | " MCR106-1 | " | 1 | CR6 | | |

NOTES:

DATE: 11-14-74
DRAWN: RHE
CHK:

# MATERIAL LIST

datum inc.

JOB NO:
QUANTITY:

REV C

TITLE: POWER SUPPLY +5V, ±15V

ASS'Y NO: 16280-3

SHT 2 OF 3

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | REF. DES. | UNIT COST | LOT TOTAL |
|---|---|---|---|---|---|---|---|
| 27 | 0510-0447 | BRIDGE RECT VS447 | DATUM | 1 | CR51 | | |
| 28 | " -0820 | DIODE MR820 | " | 1 | CR2 | | |
| 29 | " -4720-1 | " IN4720 | " | 1 | CR1 | | |
| 30 | " -4934 | " IN4934 | " | 2 | CR2,8 | | |
| 31 | | | | | | | |
| 32 | 0550-035A | TRANSISTOR TIP-35A | " | 1 | Q1 | | |
| 33 | " -7705 | " 2N3565 | " | 1 | Q4 | | |
| 34 | 0555-6005 | " 2N2905A | " | 1 | Q2 | | |
| 35 | " -6600 | " 2N3645 | " | 1 | Q3 | | |
| 36 | | | | | | | |
| 37 | 0601-6045 | CHOKE | " | 1 | L1 | | |
| 38 | " -6082 | TRANSFORMER | " | 1 | T1 | | |
| 39 | | | | | | | |
| 40 | 0702-0010-1 | FUSE 1A S/B 3AG | " | 1 | F1 | | |
| 41 | | | | | | | |
| 42 | 0750-0200 | " HOLDER | " | 1 | XF1 | | |
| 43 | | | | | | | |
| 44 | 1704-1061-1 | CONNECTOR AC | " | 1 | | | |
| 45 | | | | | | | |
| 46 | 1706-0033 | EYELET | " | 2 | (L1) | | |
| 47 | 1708-3897 | SOCKET 14P W/W | " | 1 | | | |
| 48 | " -8000 | " 8P | " | 1 | XA1 | | |
| 49 | | | | | | | |
| 50 | | | | | | | |
| 51 | 2310-1247-09 | STANDOFF | " | 1 | (L1) | | |
| 52 | 2325-1004 | TOROID RETAINER | " | 2 | (L1) | | |

NOTES:

DATE: 11-14-74
DRAWN: RHE
CHK:

# MATERIAL LIST

datum inc.

JOB NO:
QUANTITY:

REV C

TITLE: POWER SUPPLY +5V, ±15V

ASS'Y NO: 16280-3

SHT 3 OF 3

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | REF. DES. | UNIT COST | LOT TOTAL |
|---|---|---|---|---|---|---|---|
| 53 | 204561 | MTG PLATE STK | DATUM | 1 | | | |
| 54 | 204562 | SIDE BRKT STK | " | 1 | | | |
| 55 | 207350 | HEATSINK | " | 1 | | | |
| 56 | 204966-1 | MTG BRKT STK | " | 1 | | | |
| 57 | 204966-2 | " " STK | " | 2 | | | |
| 58 | | | | | | | |
| 59 | 170778 | PC BOARD STK | " | 1 | | | |
| 60 | 170779 | " " STK | " | 1 | | | |

NOTES:

DATE: 4-18-75
DRAWN: RHC
CHK:

# MATERIAL LIST

datum inc.

JOB NO:
QUANTITY:
TITLE: REGULATOR
ASS'Y NO: 17573 S'

REV
SHT 1 OF 2

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | REF. DES. | UNIT COST | LOT TOTAL |
|---|---|---|---|---|---|---|---|
| 1 | 0102-0220 | RESISTOR 22Ω 1/4W 5% | DATUM | 1 | R3 | | |
| 2 | " -0680 | " 68Ω " " | " | 2 | R1,10 | | |
| 3 | " -0101 | " 100Ω " " | " | 1 | R11 | | |
| 4 | " -0332 | " 3.3K " " | " | 1 | R9 | | |
| 5 | " -0682 | " 6.8K " " | " | 1 | R7 | | |
| 6 | " -0473 | " 47K " " | " | 2 | R4,5 | | |
| 7 | " -0754 | " 750K " " | " | 1 | R2 | | |
| 8 | 0125-0R10 | " 1Ω 3W 1% | " | 1 | R6 | | |
| 9 | 0154-1001 | " POT 1K | " | 1 | R8 | | |
| 10 | | | | | | | |
| 11 | 0212-0223 | CAPACITOR .022μf 100V | " | 1 | C6 | | |
| 12 | 0220-0476 | " 47μf 35V | " | 1 | C1 | | |
| 13 | " -0107 | " 100μf 10V | " | 1 | C4 | | |
| 14 | 0226-0104 | " .1μf " | " | 2 | C5,7 | | |
| 15 | | | | | | | |
| 16 | 0301-9305 | IC LM305H | " | 1 | A1 | | |
| 17 | | | | | | | |
| 18 | 0500-0306 | DIODE 1N914A | " | 1 | CR2 | | |
| 19 | 0515-0752-1 | " 1N752A | " | 1 | CR5 | | |
| 20 | 0540-0106-1 | " MCR106-1 | " | 1 | CR6 | | |
| 21 | " -3880 | " 1N3880R | " | 1 | CR1 | | |
| 22 | | | | | | | |
| 23 | 0550-3715 | TRANSISTOR 2N3715 | " | 1 | Q1 | | |
| 24 | " -7705 | " 2N3565 | " | 1 | Q4 | | |
| 25 | 0555-6005 | " 2N2905A | " | 1 | Q2 | | |
| 26 | " -6600 | " 2N3645 | " | 1 | Q3 | | |

NOTES:

DF4

DATE: 7-18-73
DRAWN: RKE
CHK:

# MATERIAL LIST

datum inc.

JOB NO:
QUANTITY:
TITLE: REGULATOR
ASS'Y NO: 17523S

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | REF. DES. |
|---|---|---|---|---|---|
| 27 | 0601-6085 | CHOKE | DATUM | 1 | L1 |
| 28 | | | | | |
| 29 | 1704-1625-09 | CONNECTOR 9P | " | 1 | |
| 30 | 1706-0033 | EYELET | " | 4 | (CR1, L1) |
| 31 | " -2534 | BUSHING | " | 2 | (Q1) |
| 32 | 1708-5086-5 | SOCKET COMP LEAD | " | 2 | (Q1) |
| 33 | " -8000 | " 8P | " | 1 | (A1) |
| 34 | 1792-1560 | CONTACT PIN | " | 4 | |
| 35 | | | | | |
| 36 | 2310-1246-09 | STANDOFF 6-32 x 1/8 | " | 1 | (L1) |
| 37 | " -1300-11 | " 4-40 x 1/4 | " | 2 | (Q1) |
| 38 | 2325-1004 | RETAINER | " | 2 | (L1) |
| 39 | | | | | |
| 40 | 171102 | PC BOARD STK | " | 1 | |
| 41 | | | | | |
| 42 | 705213 | HEAT SINK STK | " | 1 | |

NOTES:

DATE: 3-25-77
DRAWN: RHE
CHK:

# MATERIAL LIST

datum inc.

JOB NO:
QUANTITY
REV: C

TITLE: BATTERY CHARGER
ASS'Y NO: 15415
SHT 1 OF 1

| ITEM | STOCK/PART NO. | DESCRIPTION | MFR/SPEC | QTY. | REF. DES. | UNIT COST | LOT TOTAL |
|---|---|---|---|---|---|---|---|
| 1 | RC07GF3R01 | RESISTOR 3Ω 1/4W 5% | 81349 | 1 | R3 | | |
| 2 | 0102-0202 | " 2K " " | DATUM | 2 | R8,11 | | |
| 3 | " -0822 | " 8.2K " " | " | 1 | R10 | | |
| 4 | " -0103 | " 10K " " | " | 2 | R7,9 | | |
| 5 | 0104-01R0 | " 1Ω 1/2W " | " | 1 | R2 | | |
| 6 | 0115-1501 | " 1.5K 1/4W 1% | " | 1 | R6 | | |
| 7 | " -2152 | " 21.5K " " | " | 1 | R4 | | |
| 8 | 0154-0100 | " POT 10Ω | " | 1 | R1 | | |
| 9 | " -1001 | " " 1K | " | 1 | R5 | | |
| 10 | | | | | | | |
| 11 | 0220-0475 | CAPACITOR 4.7MF 35V | " | 1 | C2 | | |
| 12 | 0225-0101 | " 100PF | " | 1 | C1 | | |
| 13 | | | | | | | |
| 14 | 0301-9205 | IC LM205H | " | 1 | A1 | | |
| 15 | | | | | | | |
| 16 | 0540-0105 | DIODE 1N4005 | " | 1 | CR1 | | |
| 17 | " -4720-1 | " 1N4720 | " | 1 | CR2 | | |
| 18 | | | | | | | |
| 19 | 0550-0491 | TRANSISTOR MJ491 | " | 1 | Q1 | | |
| 20 | 0555-6600 | " 2N3645 | " | 3 | Q2-4 | | |
| 21 | | | | | | | |
| 22 | 1706-2534 | BUSHING | " | 2 | | | |
| 23 | 2310-1300-09 | STANDOFF 4-40X 1/8 | " | 2 | | | |
| 24 | | | | | | | |
| 25 | 170372 | PC BOARD STK | " | 1 | | | |
| 26 | 703640 | HEATSINK STK | " | 1 | | | |

NOTES:

BISHOP GRAPHICS/ACCUPRESS
REORDER NO. A-7967

www.manualsplus.com
1000318

DATUM, INC. Timing Division • 1363 State College Avenue • Anaheim, California 92806 • 714/533-6333